

(19)



Europäisches Patentamt
European Patent Office
Office européen des brevets



(11)

EP 0 700 178 A2

(12)

EUROPEAN PATENT APPLICATION

(43) Date of publication:
06.03.1996 Bulletin 1996/10

(51) Int. Cl.⁶: H04B 10/18

(21) Application number: 95112153.2

(22) Date of filing: 02.08.1995

(84) Designated Contracting States:
DE FR GB

(30) Priority: 02.08.1994 JP 181013/94
17.03.1995 JP 59295/95
18.07.1995 JP 181929/95

(71) Applicant: FUJITSU LIMITED
Kawasaki-shi, Kanagawa 211 (JP)

(72) Inventors:
• Ishikawa, George,
c/o Fujitsu Limited
Kawasaki-shi, Kanagawa 211 (JP)
• Nishimoto, Hiroshi,
c/o Fujitsu Limited
Kawasaki-shi, Kanagawa 211 (JP)

• Ooi, Hiroki,
c/o Fujitsu Limited
Kawasaki-shi, Kanagawa 211 (JP)
• Sekiy, Motoyoshi,
c/o Fujitsu Limited
Kawasaki-shi, Kanagawa 211 (JP)
• Tomofuji, Hiroaki,
c/o Fujitsu Limited
Kawasaki-shi, Kanagawa 211 (JP)


(74) Representative: Lehn, Werner, Dipl.-Ing. et al
Hoffmann, Eitle & Partner,
Patentanwälte,
Arabellastrasse 4
D-81925 München (DE)

(54) Optical transmission system with optimisation of transmission conditions

(57) The invention provides a technique for optimizing transmission conditions to achieve large-capacity transmission, and also provides peripheral techniques for the practical implementation of optical multiplexing that makes large-capacity transmission possible. A transmission characteristic is measured in a transmission characteristic measuring section (53), and control of signal light wavelength in a tunable light source (44), control of the amount of prechirping, control of the amount of dispersion compensation, and/or control of

optical power are performed to achieve the best transmission characteristic. Wavelength dispersion is deliberately introduced by a dispersion compensator, to reduce nonlinear effects. A tunable laser is used to optimize signal light wavelength for each optical amplification repeater section. Peripheral techniques, such as drift compensation, clock extraction, optical signal channel identification, clock phase stabilization, etc., are provided for the implementation of optical multiplexing.

Fig. 4



EP 0 700 178 A2

Description

BACKGROUND OF THE INVENTION

1. Field of the Invention

The present invention relates to an optical transmission system and its related techniques. More particularly, the invention relates to an optical transmission system having a transmission line with its transmission conditions optimized for large-capacity transmission, an optical transmission system employing an optical multiplexing technique such as optical time-division multiplexing (OTDM) to achieve large-capacity transmission, and related techniques for implementing the same.

2. Description of the Related Art

Increasing the transmission speed severely limits the transmission distance because of the waveform distortion, caused by group-velocity dispersion (GVD), in optical fibers. Furthermore, when the transmission speed is increased, the optical power for transmission needs to be increased to maintain required difference between transmitted and received optical power levels. This in turn increases the effect of self-phase modulation (SPM), a nonlinear effect of optical fibers, which further complicates the waveform degradation through interaction with group velocity dispersion (SPM-GVD effect).

When the waveform distortion caused by the SPM-GVD effect is dominant, the scaling rule expressed by the following equation essentially holds.

$$DB^2P_{av}L^2 = \text{const.} \quad (1)$$

D: dispersion value (ps/nm/km)

B: transmission rate (Gb/s)

P_{av} : average optical power through transmission line (mW)

L: transmission distance (km)

const.: determined by required penalty

For example, when the transmission rate B is quadrupled from 10 Gb/s to 40 Gb/s, the average optical power P_{av} through the transmission line needs to be quadrupled. This means that to achieve the same transmission distance, the dispersion value D at signal wavelength must be set to 1/64.

To minimize the dispersion value of signal light, work is currently under way to transmit signals in the 1.55- μm range by using a dispersion-shifted fiber (DSF), an optical fiber whose zero-dispersion wavelength λ_0 is shifted to the 1.55- μm range where fiber transmission loss is minimum. The zero-dispersion wavelength λ_0 is the wavelength at which the chromatic dispersion value D (ps/nm/km), representing the amount of change of propagation delay time with respect to slight variations in wavelength, changes from negative (normal dispersion) to positive (abnormal dispersion). Near this wavelength λ_0 , the absolute value of chromatic dispersion becomes the smallest, so that the waveform distortion due to the chromatic dispersion is reduced to a minimum.

However, since the fiber drawing process introduces slight variations in fiber core diameter, the zero-dispersion wavelength λ_0 of a DSF transmission line is inevitably subjected to variations along its longitudinal direction. Furthermore, transmission cables are fabricated by connecting segments of multi-core cables, each segment extending several kilometers, and the wavelengths λ_0 between adjacent segments are not continuous but randomly distributed. Moreover, λ_0 varies with aging and due to changes in ambient temperature, etc.

Therefore, in the prior art, the worst-case design has been employed by which the transmission line has been designed by considering the distribution of λ_0 and the deterioration with time so that the required transmission quality can be satisfied even if the worst-case value is applied throughout the transmission line. This has inevitably increased transmission line costs, which has impeded the implementation of high-capacity transmission systems.

On the other hand, signal processing, such as modulation and demodulation of optical signals, is usually performed at the electrical signal level, and it has been standard practice to increase the speed of optical transmission systems by increasing the speed of electrical signals used to modulate optical signals. In recent years, however, increasing the speed at the electrical signal level using electronic devices has been posing a difficult problem. Research and development is being undertaken on optical communication devices, at 10 to 40 Gb/s, using Si, GaAs, HBT, HEMT, etc., but it is said that at the present state of technology, 10 to 20 Gb/s is the maximum for practical implementation.

Therefore, to increase the transmission speed of optical transmission systems beyond the operating speeds of electronic devices, multiplexing techniques in the optical region provide effective means. There are two main techniques that can be used: one is wavelength-division multiplexing (WDM) and the other is optical time-division multiplexing (OTDM). For practical implementation of either technique, development of related peripheral techniques is needed.

SUMMARY OF THE INVENTION

Accordingly, it is a first object of the invention to provide a technique for optimizing transmission conditions to achieve high-capacity transmission.

It is a second object of the invention to provide peripheral techniques for the practical implementation of optical multiplexing that makes large-capacity transmission possible.

According to the present invention, there is provided an optical transmission system comprising: an optical transmitter for generating an optical signal; an optical transmission line for transmitting the optical signal generated by the optical transmitter; an optical receiver for recognizing the optical signal transmitted over the optical transmission line; and characteristic adjusting means for adjusting at least either a characteristic value of the optical signal or a characteristic value of the optical transmission line, and thereby matching the characteristic of the optical signal to that of the optical transmission line.

According to the present invention, there is also provided an optical transmission system comprising: an optical transmitter for generating an optical signal; an optical transmission line for transmitting the optical signal generated by the optical transmitter; an optical receiver for recognizing the optical signal transmitted over the optical transmission line; and means for reducing a nonlinear effect by smoothing variation of the power of the optical signal transmitted through the optical transmission line.

According to the present invention, there is also provided an optical transmission system comprising: an optical transmitter for generating an optical signal; an optical transmission line for transmitting the optical signal generated by the optical transmitter; an optical receiver for recognizing the optical signal transmitted over the optical transmission line; an optical amplification repeater, installed at an intermediate point along the optical transmission line, for optically amplifying the optical signal being transmitted along the optical transmission line; and a wavelength converter for converting the wavelength of the optical signal optically amplified in the optical amplification repeater.

According to the present invention, there is also provided a drift compensation circuit for optical modulators in an optical multiplexing system in which a plurality of optical signals modulated with baseband signals by a plurality of optical modulators are multiplexed together, comprising: a plurality of drive circuits for amplitude-modulating the baseband signals with low-frequency signals before the baseband signals are supplied to the plurality of optical modulators; an optical coupler for separating a portion of an optical multiplexed signal generated by multiplexing the plurality of optical signals; an optical detector for converting the portion of the optical multiplexed signal separated by the optical coupler into an electrical signal; and control means for generating a bias signal for the drift compensation of each of the optical modulators by phase-detecting the low-frequency signal components contained in the output of the optical detector with the low-frequency signals respectively used in the plurality of drive circuits.

According to the present invention, there is also provided an optical transmission system comprising: optical time-division multiplexing means for time-division multiplexing a plurality of optical signals; an optical transmission line for transmitting an optical multiplexed signal generated by the optical time-division multiplexing means; clock extraction means for extracting a clock signal for the original optical signals directly from the optical multiplexed signal transmitted over the optical transmission line; and amplitude difference providing means for providing amplitude differences among the optical signals multiplexed on the optical multiplexed signal to be supplied to the clock extraction means and thereby enabling the clock extraction means to extract the clock signal.

According to the present invention, there is also provided an optical transmitter comprising: optical time-division multiplexing means for time-division multiplexing a plurality of optical signals; and amplitude difference providing means for providing amplitude differences among the optical signals to be multiplexed on an optical multiplexed signal so that a clock signal for the original optical signals can be extracted directly from the optical multiplexed signal at the receiving end.

According to the present invention, there is also provided an optical transmission system comprising: optical time-division multiplexing means for time-division multiplexing a plurality of optical signal channels; means for appending identification information, for identifying each optical signal channel, to an optical multiplexed signal generated by the optical time-division multiplexing means; an identification information extraction circuit for extracting the identification information contained in the optical signal channel; and a control circuit for changing output destinations so that each optical signal channel is output to a designated destination in accordance with the identification information extracted by the identification information extraction circuit.

According to the present invention, there is also provided an optical receiver comprising: an identification information extraction circuit for extracting the identification information contained in the optical signal channel; and a control circuit for changing output destinations so that each optical signal channel is output to a designated destination in accordance with the identification information extracted by the identification information extraction circuit.

According to the present invention, there is also provided an optical transmitter comprising: optical time-division multiplexing means for time-division multiplexing a plurality of optical signal channels; and means for appending identification information for identifying each optical signal channel, to an optical multiplexed signal generated by the optical time-division multiplexing means.

According to the present invention, there is also provided an optical receiver for receiving an optical time-division multiplexed signal carrying a plurality of optical signals time-division multiplexed thereon and having a low-frequency signal superimposed thereon in a time slot designated for a specific optical signal, comprising: an optical switch for separating the optical time-division multiplexed signal into the respective optical signals; clock generating means for generating a clock signal for controlling the optical switch; and clock phase control means for performing control so that the clock signal generated by the clock generating means is phase synchronized, to the optical time-division multiplexed signal, by using the low-frequency signal superimposed on the optical time-division multiplexed signal.

BRIEF DESCRIPTION OF THE DRAWINGS

Figure 1 is a block diagram showing an example of an optical transmission system according to the present invention, in which a tunable light source is provided;

Figure 2 is a perspective view showing a tunable semiconductor laser as an example of the tunable light source;

Figure 3 is a block diagram showing another example of the optical transmission system according to the present invention, further including a tunable filter for each repeater;

Figure 4 is a block diagram showing another example of the optical transmission system according to the present invention, further including a transmission characteristic measuring section;

Figure 5 is a diagram for explaining a method of determining wavelength from a measured value of a bit-error rate;

Figure 6 is a diagram for explaining the measurement of a transmission characteristic using an eye pattern;

Figure 7 is a diagram for explaining a Q value;

Figure 8 is a diagram showing another example of the optical transmission system according to the present invention;

Figure 9 is a diagram showing another example of the optical transmission system according to the present invention;

Figure 10 is a diagram showing an example of the optical transmission system according to the present invention, in which a variable dispersion compensator is installed at transmitting end;

Figure 11 is a diagram showing another example of the optical transmission system according to the present invention;

Figure 12 is a diagram showing an example of the optical transmission system according to the present invention, in which a variable dispersion compensator is installed at receiving end;

Figure 13 is a diagram showing another example of the optical transmission system according to the present invention;

Figure 14 is a diagram showing an example of the optical transmission system according to the present invention, in which a variable dispersion compensator is also installed at repeater;

Figure 15 is a diagram showing an example of the optical transmission system according to the present invention, further including a transmission characteristic measuring section;

Figure 16 is a diagram showing another example of the optical transmission system according to the present invention;

Figure 17 is a diagram showing another example of the optical transmission system according to the present invention;

Figure 18 is a diagram showing another example of the optical transmission system according to the present invention;

Figure 19 is a diagram showing another example of the optical transmission system according to the present invention;

Figure 20 is a diagram showing a characteristic of a Mach-Zehnder optical modulator;

Figure 21 is a diagram for explaining red shift and blue shift in the Mach-Zehnder optical modulator;

Figure 22 is a diagram showing a Mach-Zehnder optical modulator in which an intensity modulator and a phase modulator are connected in tandem to control the amount of pre-chirping;

Figure 23 is a diagram showing an example of signal light wavelength spacing in wavelength multiplexing;

Figure 24 is a diagram showing the temperature dependence of zero dispersion wavelength λ_0 ;

Figure 25 is a diagram showing an example of temperature evaluation for an optical fiber;

Figure 26 is a diagram showing another example of temperature evaluation for an optical fiber;

Figure 27 is a diagram showing another example of temperature evaluation for an optical fiber;

Figure 28 is a diagram showing an example of an optical transmission system in which the signal light wavelength is changed on the basis of temperature evaluation;

Figure 29 is a diagram showing another example of the optical transmission system according to the present invention;

Figure 30 is a diagram showing an example of an optical transmission system in which the amount of prechirping is changed on the basis of temperature evaluation;

Figure 31 is a diagram showing an example of an optical transmission system in which the amount of dispersion compensation is changed on the basis of temperature evaluation;

Figure 32 is a diagram showing an example of an optical transmission system in which a variable dispersion compensator is installed at a receiving end;

Figure 33 is a diagram showing an example of an optical transmission system in which variable dispersion compensators are installed at both a transmitter and a receiver and also at a repeater;

Figure 34 is a diagram showing an example of an optical transmission system in which the degree of amplification in an optical amplifier is changed on the basis of temperature evaluation;

Figure 35 is a diagram showing an example of an optical transmission system in which the signal light wavelength, the amount of prechirping, the amount of dispersion compensation, and the degree of amplification are changed on the basis of temperature evaluation;

Figure 36 is a diagram showing an example of an optical transmission system in which a nonlinear effect is reduced by installing a dispersion compensator at receiving end;

Figure 37 is a diagram showing another example of the optical transmission system;

Figure 38 is a diagram showing an example of an optical transmission system in which a dispersion compensator is installed at a transmitting end;

Figure 39 is a diagram showing another example of the optical transmission system;

Figure 40 is a diagram showing an example of an optical transmission system in which the compensation amount D in the dispersion compensator installed at a receiving end is set to a positive value;

Figure 41 is a diagram showing an example of an optical transmission system in which the compensation amount D in the dispersion compensator installed at a receiving end is set to a negative value;

Figure 42 is a diagram showing an example of an optical transmission system in which dispersion compensators with dispersion amounts with signs opposite to each other are installed at a transmitting end and a receiving end;

Figure 43 is a diagram showing an example of an optical transmission system in which a dispersion compensator is also installed at a repeater;

Figure 44 is a diagram showing an example of an optical transmission system in which a dispersion compensator is installed and further, a transmission characteristic is measured, to optimize the signal light wavelength;

Figure 45 is a diagram showing an example of an optical transmission system in which a dispersion compensator is installed at a transmitting end;

Figure 46 is a diagram showing an example of an optical transmission system in which dispersion compensators are installed at both a transmitter and a receiver and also at a repeater;

Figure 47 is a diagram showing an example of an optical transmission system in which a dispersion compensator is installed and, further, a transmission characteristic is measured, to control the amount of prechirping to an optimum value;

Figure 48 is a diagram showing an example of an optical transmission system in which a dispersion compensator is installed at a transmitting end;

Figure 49 is a diagram showing an example of an optical transmission system in which dispersion compensators are installed at both a transmitter and a receiver and also at a repeater;

Figure 50 is a diagram showing an example of an optical transmission system in which a dispersion compensator is installed and further, a transmission characteristic is measured, to control the signal light wavelength and the amount of prechirping to optimum values;

Figure 51 is a diagram showing an example of an optical transmission system in which a dispersion compensator is installed at a transmitting end;

Figure 52 is a diagram showing an example of an optical transmission system in which dispersion compensators are installed at both a transmitter and a receiver and also at a repeater;

Figure 53 is a diagram showing an example of an optical transmission system in which a wavelength converter is installed at an optical amplification repeater;

Figure 54 is a diagram showing an example of an optical transmission system in which the wavelength is also made variable in the transmitter;

Figure 55 is a cross-sectional view of a wavelength converting laser as an example of the wavelength converter;

Figure 56 is a diagram showing an example of an optical transmission system in which a transmission characteristic is measured to optimize the signal light wavelength for each optical amplification repeater section;

Figure 57 is a diagram showing an example of an optical transmission system in which a dispersion compensator is installed;

Figure 58 is a diagram for explaining the operation of a drift compensation circuit with a proper operating point;

Figure 59 is a diagram for explaining the operation of the drift compensation circuit when the operating point has shifted;

Figure 60 is a diagram for explaining the operation of the drift compensation circuit when the operating point has shifted;

Figure 61 is a block diagram showing an example of an optical multiplexing transmission system having a drift compensation circuit of the present invention;

Figure 62 is a block diagram showing another example of the optical multiplexing transmission system having a drift compensation circuit of the present invention;

Figure 63 is a block diagram showing another example of the optical multiplexing transmission system having a drift compensation circuit of the present invention;

Figure 64 is a block diagram showing another example of the optical multiplexing transmission system having a drift compensation circuit of the present invention;

Figure 65 is a block diagram showing another example of the optical multiplexing transmission system having a drift compensation circuit of the present invention;

Figure 66 is a block diagram showing another example of the optical multiplexing transmission system having a drift compensation circuit of the present invention;

Figure 67 is a block diagram showing another example of the optical multiplexing transmission system having a drift compensation circuit of the present invention;

Figure 68 is a block diagram showing another example of the optical multiplexing transmission system having a drift compensation circuit of the present invention;

Figure 69 is a block diagram showing another example of the optical multiplexing transmission system having a drift compensation circuit of the present invention;

Figure 70 is a block diagram showing an example of an optical time-division multiplexing system to which a technique of clock extraction according to the present invention is applied;

Figure 71 is a timing chart for explaining the operation of the system shown in Figure 70;

Figure 72 is a waveform diagram for explaining the clock extraction technique of the present invention;

Figure 73 is a waveform diagram for explaining another example of the clock extraction technique of the present invention;

Figure 74 is a block diagram showing an example of an optical transmitter according to the present invention;

Figure 75 is a block diagram showing another example of the optical transmitter according to the present invention;

Figure 76 is a block diagram showing another example of the optical transmitter according to the present invention;

Figure 77 is a diagram for explaining how light output strength changes when the amplitude of a drive voltage for a Mach-Zehnder optical modulator is changed;

Figure 78 is a diagram for explaining how light output strength changes when the bias of a drive voltage for a Mach-Zehnder optical modulator is changed;

Figure 79 is a block diagram showing another example of the optical transmitter according to the present invention;

Figure 80 is a block diagram showing an example of an optical receiver according to the present invention;

Figure 81 is a block diagram showing another example of the optical receiver according to the present invention;

Figure 82 is a block diagram showing the details of a clock extraction circuit;

Figure 83 is a block diagram showing an example of an optical demultiplexer according to the present invention;

Figure 84 is a diagram showing an example of a transmission data format containing channel identification data;

Figure 85 is a block diagram showing another example of an optical demultiplexer according to the present invention;

Figure 86 is a block diagram showing another example of an optical demultiplexer according to the present invention;

Figure 87 is a block diagram showing another example of an optical demultiplexer according to the present invention;

Figure 88 is a diagram showing an example of an optical delay circuit;

Figure 89 is a block diagram showing another example of an optical demultiplexer according to the present invention;

Figure 90 is a diagram showing a low-frequency signal multiplexed on an optical signal;

Figure 91 is a block diagram showing another example of an optical demultiplexer according to the present invention;

Figure 92 is a block diagram showing another example of an optical demultiplexer according to the present invention;

Figure 93 is a block diagram showing another example of an optical demultiplexer according to the present invention;

Figure 94 is a block diagram showing an example of an optical transmitter according to the present invention;

Figure 95 is a block diagram showing another example of an optical transmitter according to the present invention;

Figure 96 is a circuit diagram showing the details of drive circuits 418 and 420;

Figure 97 is a block diagram showing an optical receiver in which clock phase stabilization control is performed according to the present invention;

Figure 98 is a timing chart for explaining the operation of the circuit shown in Figure 97;

Figure 99 is a diagram for explaining phase difference θ ;

Figure 100 is a diagram showing the relationship between phase difference θ and f_1 component strength;

Figure 101 is a block diagram showing another example of an optical receiver according to the present invention;

Figure 102 is a block diagram showing another example of an optical receiver according to the present invention;

Figure 103 is a block diagram showing another example of an optical receiver according to the present invention;

Figure 104 is a diagram showing an example of a low-frequency signal superimposed on a received signal in the optical receiver shown in Figure 103;

Figure 105 is a block diagram showing another example of an optical receiver according to the present invention;

Figure 106 is a block diagram showing an example of a detailed configuration of a timing regenerator;

Figure 107 is a waveform diagram showing an example of an optical multiplexed signal;

Figure 108 is a diagram showing a characteristic of an optical detector;

Figure 109 is a block diagram showing another example of a detailed configuration of the timing regenerator;

Figure 110 is a block diagram showing the details of an optical switch;

Figure 111 is a block diagram showing another example of an optical receiver according to the present invention;

Figure 112 is a diagram showing the relationship of a synchronous detection output value relative to the phase difference θ ;

Figure 113 is a diagram showing an example of a circuit for detecting an input-off alarm condition;

Figure 114 is a block diagram showing another example of an optical receiver according to the present invention;

Figure 115 is a timing chart explaining an operation of the circuit of Figure 86;

Figure 116 is a block diagram showing an example of an optical exchange according to the present invention;

Figure 117 is a block diagram showing another example of an optical exchange according to the present invention;

Figure 118 is a block diagram showing another example of an optical exchange according to the present invention;

Figure 119 is a block diagram showing another example of an optical exchange according to the present invention;

and

Figure 120 is a waveform diagram showing the operation of the circuit of Figure 96.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

Figure 1 is a block diagram showing an example of an optical signal transmission system according to the present invention. In Figure 1, reference numeral 11 is an optical transmitter, 12 is an optical receiver, 13 is an optical fiber, 14 is tunable light source, 15 is a tunable filter, 16 and 17 are optical amplifiers or optical repeaters including optical amplifiers, 18 is an optical detector, and 19 is a drive circuit.

The tunable light source 14 used in the optical transmitter 11 can be constructed, for example, from a tunable semiconductor laser of known configuration, such as a three-electrode type or an external diffraction grating controlled type.

Figure 2 is a diagram for explaining a tunable semiconductor laser; the basic structure of a three-electrode tunable semiconductor laser is shown here. The tunable semiconductor laser shown in Figure 2 has an InGaAsP/InP laser configuration. As shown, a laser oscillation region 27 containing an active layer 25 is formed between a common electrode 21 and an electrode 22, a wavelength fine-adjusting region 28 is formed between the common electrode 21 and an electrode 23, and a wavelength coarse-adjusting region 29 containing a diffraction grating 26 is formed between the common electrode 21 and an electrode 24. The emission wavelength can be varied by adjusting a current I_p applied to the electrode 23 and a current I_d applied to the electrode 24, and the optical output can be controlled by adjusting a current I_a applied to the electrode 22. Therefore, by controlling the currents I_a , I_p , and I_d via the drive circuit 19, the emission wavelength can be controlled while outputting an optical signal modulated with the information to be transmitted.

Instead of the direct modulation type described above that directly drives the light source, the tunable light source 14 may be constructed as an external modulation type which uses an external modulator to modulate the light from the light source. Furthermore, an optical amplifier may be provided for amplifying an optical signal from the tunable light source 14 for transmission through the optical fiber 13.

The optical amplifiers 16 and 17 can be constructed from optical-fiber amplifiers doped with rare earth elements such as Er, Nd, etc. For example, an Er-doped optical-fiber amplifier can directly amplify an optical signal at 1.5 μm when pumped with light at 1.48 μm or 0.98 μm .

The optical receiver 12 consists, for example, of the optical amplifier 17, tunable filter 15, and optical detector 18. The optical amplifier 17 and the tunable filter 15 may be omitted. The optical detector 18 is constructed, for example, from a photodiode or a phototransistor of known structure for converting an optical signal into an electrical signal. An information processing section for converting the signal to electrical form by the optical detector 18, performing equalization for level discrimination, and recovering the transmitted information for reception, is not shown here since it can be implemented using various known configurations.

The tunable filter 15 can be constructed using a filter of known configuration. For example, it is possible to use a temperature-controlled tunable filter as explained by the title "Study of a Fabry-Perot wavelength-selective optical filter using Si," B-1055, Proc., Institute of Electronics, Information and Communication Engineers, Spring Convention, 1994. It is also possible to use a fixed-wavelength filter having a transmission wavelength characteristic that can cover the entire wavelength variable range of the tunable light source 14.

In a system in which the optical transmitter 11 and the optical receiver 12 are not separated by a large distance, the optical amplifiers 16 can be omitted, in which case the optical transmitter 11 will be connected to the optical receiver 12 by the optical fiber 13 alone. If there exists a fluctuation in the zero dispersion wavelength along the longitudinal direction of the optical fiber 13, or if there exist variations in the zero dispersion wavelength of the optical fiber 13 between fiber segments constructed by splicing manufactured unit lengths of optical fibers, the average value of such fluctuation or variation of the zero dispersion wavelength is obtained along the entire length between the optical transmitter 11 and

the optical receiver 12, and the tunable light source 14 is so regulated as to emit light at that wavelength, for example. It should be noted that a signal light wavelength that provides the best transmission characteristics is not always the zero dispersion wavelength, as explained later.

When an optical signal is amplified by a rare-earth doped optical-fiber amplifier and fed into an optical fiber for transmission over a long distance, if the wavelength of the signal light is in an abnormal dispersion region near the zero dispersion wavelength of the optical fiber, a four-wave mixing (FWM) phenomenon occurs between the signal light and spontaneously emitted light, and because of modulation instability the spontaneous emission is amplified, degrading the S/N ratio. To prevent this, the emission wavelength is controlled within a normal dispersion region, while avoiding a region near the zero dispersion wavelength of the optical fiber 13.

For a long distance transmission system, the optical amplifiers 16 and 17 are usually provided. Since the optical amplifiers 16 and 17 not only amplify optical signals but emit light as spontaneous emission, it is desirable to provide a filter in the front stage of the optical receiver 18. It is further desirable that the filter be constructed from the tunable filter 15 whose transmission wavelength characteristic is adjustable. In that case, when the emission wavelength of the tunable light source 14 of the optical transmitter is controlled in the above manner, the transmission characteristics can be further improved by controlling the transmission wavelength characteristic of the tunable filter 15 in such a manner as to match the emission wavelength.

Figure 3 is a block diagram showing another example of the optical signal transmission system according to the present invention. In Figure 3, reference numeral 30 is a repeater, 31 is an optical transmitter, 32 is an optical receiver, 33 is an optical fiber, 34 is a tunable light source, 35 is a tunable filter, 36 and 37 are optical direct amplifiers, 38 is an optical detector, 39 is a drive circuit, and 40 is a tunable filter. The parts with the same names as those in the embodiment shown in Figure 1 have the same functions as the corresponding parts already described.

In the example shown here, the optical amplifier 36, such as a rare-earth doped optical-fiber amplifier, and the tunable filter 40 constitute the repeater 30. The wavelength transmission characteristic of the tunable filter 40 in each repeater 30, as with the tunable filter 35 in the optical receiver 32, is adjusted so as to block light components other than the optical signal, such as spontaneous emission from the optical amplifier 36, thus improving transmission characteristics and making long-distance transmission possible. It is also possible to use, instead of the tunable filter 40, a fixed-wavelength filter having a transmission wavelength characteristic that can cover the entire wavelength variable range of the tunable light source 34. Furthermore, in the configuration shown here, the tunable filter 40 is provided after the optical amplifier 36, but it will be recognized that the invention is not limited to this particular configuration.

Figure 4 is a block diagram showing a further example of the optical signal transmission system according to the present invention. In Figure 4, reference numeral 41 is an optical transmitter, 42 is an optical receiver, 43 is an optical fiber, 44 is a tunable light source, 45 is a tunable filter, 46 and 47 are optical amplifiers, 48 is an optical detector, 49 is a drive circuit, 50 is a tunable filter, 51 is a repeater, 52 is a sweep controller, and 53 is a transmission characteristic measuring section.

This example is identical to the embodiment shown in Figure 3, except that the transmission characteristic measuring section 53 and the sweep controller 52 are added. The drive circuit 49 is controlled by the sweep controller 52 to sweep the emission wavelength of the tunable light source 44. For example, when the tunable light source 44 is constructed from the tunable semiconductor laser shown in Figure 2, sweeping can be accomplished by varying the currents I_p and I_d ; in the case of a semiconductor laser of other configuration, sweeping of the emission wavelength can be accomplished by continuously varying the temperature. The optical signal with the thus swept emission wavelength is transmitted along the optical fiber 43 and via the repeaters 51, and is detected by the optical detector 48 of the optical receiver 42, where the received result is applied to the transmission characteristic measuring section 53 which measures the transmission characteristic between the optical transmitter 41 and the optical receiver 42. Based on the result of the transmission characteristic measurement, the emission wavelength of the tunable light source 44 and the wavelength transmission characteristics of the tunable filters 45 and 50 are so set as to achieve the best transmission characteristic.

When the system is constructed so that the tunable light source 44 and the tunable filters 45 and 50 are automatically controlled by the transmission characteristic measuring section 53, sweep control information for controlling the sweeping of the emission wavelength of the tunable light source via the drive circuit 49 is transmitted from the sweep controller 52 to the transmission characteristic measuring section 53, as shown by a dotted line. Based on the sweep control information thus transmitted, the transmission characteristic measuring section 53 controls the transmission wavelength characteristic of the tunable filters 45 and 50, as shown by dotted lines in the figure. From the transmission characteristic at the optical detector 48 during sweep control, the transmission characteristic measuring section 53 determines the emission wavelength that maximizes the transmission characteristic, and sends control information to the drive circuit 49 to control the wavelength to the determined value, while applying control information to the tunable filters 45 and 50 to control their transmission wavelength characteristics to match that emission wavelength.

Therefore, by activating the sweep controller 52 when the system is started, the emission wavelength of the tunable light source 44 can be automatically set to a value that provides the best transmission characteristics. Further, while the system is in operation, the sweep controller 52 may be deactivated, but it would be possible to have the transmission characteristic measuring section 53 measure the transmission characteristic periodically or continuously and adjust the

emission wavelength of the tunable light source 44 and the wavelength transmission characteristics of the tunable filters 45 and 50 so that the best transmission characteristic can be achieved.

The control signal for adjusting the wavelength transmission characteristic from the transmission characteristic measuring section 53 to each repeater 51 and the control signal applied to the drive circuit 49 for optimizing the transmission characteristic or the sweep control signal from the sweep controller 52 to the transmission characteristic measuring section 53 can be transmitted using a relatively low-speed transmission line. Therefore, such information can be transmitted over control lines or the like installed between the optical transmitter 11 and the optical receiver 12, and in the case of a system in which optical signals are transmitted in both directions, such information can be transmitting by superimposing it as a sub-signal on the main optical signal.

When the transmission characteristic measuring section 53 is constructed to measure the transmission characteristic by measuring bit-error rates, if the bit-error rate at each wavelength is measured while sweeping the emission wavelength of the tunable light source 44 and the measurements are plotted as shown in Figure 5 where the allowable error rate is set at 10^{-11} , for example, the emission wavelength of the tunable light source 44 is set approximately at the center of the wavelength range falling within the allowable error rate. That is, the drive circuit 49 is controlled to set the emission wavelength of the tunable light source 44 to the best point of the transmission characteristic, and at the same time, the wavelength transmission characteristics of the tunable filters 45 and 50 are set accordingly. The bit-error rate can thus be controlled within the allowable value despite the variation of the characteristics of the optical fiber 43 caused by temperature changes, aging, etc.

The bit-error rate can be measured using an error rate measuring means provided in an ordinary transmission system. If the transmission speed of optical signals is higher than 10 Gb/s, for example, the error rate at each wavelength can be measured in a short time for allowable error rates smaller than 10^{-11} . It is also possible to append a parity check bit for transmission and measure the error rate using the parity check bit.

The transmission characteristic measuring section 53 may be constructed to measure the transmission characteristic using an eye pattern. Figure 6 is a diagram for explaining an eye mask pattern. If the eye mask pattern shown by thick lines represents a threshold value, for example, the emission wavelength of the tunable light source 44 is adjusted so that the eye pattern of the received signal is formed outside the thick-lined eye mask pattern, that is, the eye pattern exceeds the predetermined threshold value. Since the eye pattern opens wide when the transmission characteristic is good, the emission wavelength of the tunable light source 44 may be adjusted so that the eye pattern opens widest. As an adjusting means in this case, control may be performed manually while observing the eye pattern, or alternatively, automatic control by means of computer processing may be employed.

An alternative way to measuring the bit-error rate is to measure the Q value (electrical SNR). The definition of the Q value is given below in conjunction with Figure 7.

$$Q = 20 \log_{10} [(m_1 - m_0) / (s_1 + s_0)]$$

where

μ_1 : average level during "emission"

μ_0 : average level during "no emission"

σ_1 : standard deviation of level during "emission"

σ_0 : standard deviation of level during "no emission"

The Q value is expressed using the signal level difference (= signal amplitude) between emission and no emission as the numerator and the sum of the standard deviations of noise during emission and during no emission as the denominator. When a Gaussian distribution is assumed for the noise distribution, the bit-error rate given by the Q value defined by the above equation agrees with the minimum-value of the actually measured bit-error rate. A Q value measuring system is substantially identical in configuration to the optical receiver; that is, using a discrimination circuit having a reference voltage varying function, the discrimination level of the equalizing waveform is varied up and down with respect to the optimum level to measure the bit-error rate, and by finding the intersection of the two straight lines obtained from the measurement, the minimum point of the bit-error rate is estimated, to obtain the Q value. Other methods, such as measuring the transmitted waveform and using specifications of equal bit-error rate curves, may also be employed.

Figure 8 is a block diagram showing another example of the optical signal transmission system according to the present invention. In Figure 8, reference numeral 61 is an optical transmitter, 62 is an optical receiver, 63 is an optical fiber, 64 is a tunable light source, 65 is an optical coupler, 66a and 66b are external modulators, 67a and 67b are drive circuits, 68 is an optical multiplexer, 69 and 70 are optical amplifiers, 71 is a tunable filter, 72 is an optical coupler, 73a and 73b are optical detectors, and 74 is a transmission characteristic measuring section.

As in the foregoing examples, the tunable light source 64 can be implemented using, for example, a tunable semiconductor laser. The optical coupler 65 splits the output light of the tunable light source 64 into two output signals which are respectively applied to the external modulators 66a and 66b. The optical coupler 65 may be constructed to split the light into three or more output signals to drive the respective external modulators.

Clock signals CLKa and CLKb and transmission information not shown are applied to the drive circuits 67a and 67b which then generate modulation signals synchronized to the clock signals CLKa and CLKb and apply them to the external modulators 66a and 66b for modulation of the two split light signals. The modulated light signals are multiplexed by the optical multiplexer 68 and amplified by the amplifier 69 for transmission through the optical fiber 63. The external modulators 66a and 66b can be constructed, using, for example, Mach-Zehnder optical modulators using LiNbO₃ substrates or semiconductor electro-absorption optical modulators.

Multiplexing of the optical signals in the optical multiplexer 68 can be accomplished using various multiplexing means such as bit multiplexing, byte multiplexing, frame multiplexing, etc. Modulation timing in the external modulators 66a and 66b is selected according to such multiplexing means, and control is performed so that the external modulators 66a and 66b output modulated optical signals with different phases which are then multiplexed together in the optical multiplexer 68.

If the optical coupler 65 is constructed, for example, as a Mach-Zehnder optical modulator having two separate output ports, and the output light of the tunable light source 64 is input to the optical modulator for modulation with a 10 GHz clock signal, for example, optical clock signals 180° out of phase with respect to each other are output at 10 GHz from the two respective output ports and applied to the external modulators 66a and 66b, respectively. These optical signals are modulated by the external modulators 66a and 66b with information to be transmitted, and optically multiplexed by the optical multiplexer 68 which outputs a multiplexed optical signal at a transmission rate of 20 Gb/s.

When two separate information signals are transmitted together by time-division multiplexing, it would be possible at the optical receiver 62 to demultiplex them after first converting the multiplexed signal to an electrical signal; in the above example, however, the multiplexed signal is first amplified by the optical amplifier 70, then passed through the tunable filter 71 for elimination of noise and other unwanted light components, and then fed into the optical coupler 72 where the input signal is split into two signals which are then applied to the respective optical detectors 73a and 73b. Using a clock signal from a clock regenerator not shown, two clock signals corresponding to the clock signals CLKa and CLKb used in the optical transmitter 61 are obtained, and using the thus obtained clock signals, the two transmitted information signals are reconstructed from the output signals from the optical detectors 73a and 73b.

A transmission characteristic measuring section 74 may be provided for each of the optical detectors 73a and 73b, but in the above example, one is provided for one of the detectors. When the system is started or while the system is in operation, the transmission characteristic measuring section 74 measures the transmission characteristic, sets the emission wavelength of the tunable light source 64 for the best transmission characteristic, and sets the transmission wavelength characteristic of the tunable filter 71 accordingly. This facilitates high-speed transmission over long distances. The optical amplifier 69, tunable filter 71, etc. may be omitted.

Figure 9 is a block diagram showing another example of the optical transmission system according to the present invention. In Figure 9, reference numeral 81 is an optical transmitter, 82 is an optical receiver, 83 is an optical fiber, 84 is a tunable light source, 85 is an optical coupler, 86a and 86b are external modulators, 87a and 87b are drive circuits, 88 is an optical multiplexer, 89 is an optical direct amplifier, 90 is an optical coupler, 91a and 91b are optical direct amplifiers, 92a and 92b are tunable filters, 93a and 93b are optical detectors, and 94 is a transmission characteristic measuring section.

The optical transmitter 81 is identical, in both configuration and operation, to the transmitter 61 in the foregoing embodiment. At the optical receiver 82, the optical signal received via the optical fiber 83 is split by the optical coupler 90 into two signals which are then amplified by the respective optical amplifiers 91a and 91b and applied to the optical detectors 93a and 93b through the tunable filters 92a and 92b, respectively. The two transmitted information signals are thus processed by the respective optical detectors 93a and 93b.

As in the foregoing embodiment, the transmission characteristic measuring section 94 measures the transmission characteristic between the optical transmitter 81 and the optical receiver 82 by using the output signal from one or other of the optical detectors 93a, 93b, and controls the emission wavelength of the tunable light source 84 for the best transmission characteristic, while controlling the wavelength transmission characteristics of the tunable filters 92a and 92b accordingly. High-speed transmission is thus made possible by time-division multiplexing of optical signals; furthermore, even though there exists a variation in the zero dispersion wavelength, since the emission wavelength is controlled so as to give the best transmission characteristics, the transmission distance can be extended.

It will be appreciated that the present invention is not limited to the above illustrated examples, but various modifications can be made in the invention. For example, in the embodiments shown in Figures 8 and 9, the output light of the tunable light source is divided into two signals, but it would be possible to divide it into a larger number of signals with a corresponding number of external modulators provided so that optical signals modulated with transmitted information from multiple lines would be time-division multiplexed, thereby making transmission at higher speeds possible. Further, the above embodiments have each dealt with an example in which bit multiplexing is used, but it would be possible to use other multiplexing means such as byte multiplexing or frame multiplexing. Furthermore, in the embodiments shown in Figures 8 and 9, optical amplifiers may be provided at prescribed intervals of distance along the optical fiber 63, 83 to further extend the transmission distance.

Any of the examples thus far described use a tunable light source and optimize the transmission conditions by controlling the wavelength of the signal light to an optimum value with respect to the transmission line in use. Conversely, it is possible to use a signal light of a fixed wavelength, in which case the transmission conditions are optimized for that fixed wavelength by using a variable dispersion compensator capable of adjusting the amount of wavelength dispersion. Examples of such an optical transmission system will be described below.

In the examples shown in Figures 10 and 11, the variable dispersion compensator is provided at the transmitting end, while in the examples shown in Figures 12 and 13, it is provided at the receiving end. Figures 10 and 12 each show an example of a repeaterless transmission system, and Figures 11 and 13 each show an example of a multiple optical amplifier repeated system. In the figures, reference numeral 100 is an optical transmitter, 101 is a variable dispersion compensator capable of varying the amount of dispersion, 102 is a transmission line, 103 is an optical receiver, and 104 is a repeater amplifier. In the description below, the same reference numerals indicate the same constituent parts.

The variable dispersion compensator 101 used here can be constructed from a Mach-Zehnder interferometer-type dispersion compensator using a planar lightwave circuit (PLC) (for example, Takiguchi et al., "Dispersion Compensation Experiments Using PLC-type Light Dispersion Equalizer," C-337, Institute of Electronics, Information and Communication Engineers, Spring Convention, 1994), or an optical resonator-type dispersion compensator (for example, Fukushima et al., "Study on a Dispersion Compensation Method Using an Optical Resonator," B-935, Institute of Electronics, Information and Communication Engineers, Autumn Convention, 1994).

Figure 14 shows an example of a multiple optical amplifier repeated system in which a variable dispersion compensator is also provided in each repeater. The invention, however, is not limited to the configuration shown in the example of Figure 14 where both the transmitter and receiver as well as all the repeaters are provided with variable dispersion compensators, but various other configurations are possible, for example, a configuration where only the repeaters are provided with variable dispersion compensators, a configuration where the transmitter and the repeaters are provided with variable dispersion compensators, a configuration where the repeaters and the receiver are provided with variable dispersion compensators. Furthermore, in the case where the repeaters are provided with the variable dispersion compensators, only some of the repeaters may be provided with them.

As for the dispersion compensation techniques used in the examples of Figures 10 to 14, though various dispersion compensators and dispersion compensation methods using them have already been proposed and implemented for land systems, undersea systems, repeaterless systems, and multiple repeater systems, the point of the present invention is that using a variable dispersion compensator capable of varying the amount of dispersion, the amount of dispersion compensation is optimized at a value that maximizes the transmission characteristic for each repeater section.

For optimization, when the zero dispersion wavelength of the transmission line, including the variation along the longitudinal direction, is known, the optimum dispersion compensation amount can be determined through simulation, and this amount is set in the variable dispersion compensator 101.

Figure 15 shows another example. In this example, sweeping the dispersion compensation amount is performed while measuring the transmission characteristic at the receiving end, and the variable dispersion compensator is set to a value at which a good transmission characteristic is obtained. In this example, since the variable dispersion compensator 101 is provided at the receiver, the transmission characteristic is measured at the receiving end while sweeping the dispersion compensation amount, and the optimum dispersion compensation amount is set accordingly. The same method of measurement as used in the previously described transmission characteristic measuring section 53, 74, or 94 may be used in the transmission characteristic measuring section 105 for measurement of the transmission characteristic.

Figures 16 and 17 show a still further example. In the optical transmission system of this example, a control signal is fed back to the transmitter or to the repeaters on the basis of the transmission characteristic measured at the receiver, to optimize the dispersion compensation amount that is set in the variable dispersion compensator 101 installed therein. Figure 16 shows a configuration where the variable dispersion compensator is installed only in the transmitter. In this configuration, the transmission characteristic is measured at the receiving end while the dispersion compensation amount is being swept at the transmitting end, and the resulting information is fed back so that the optimum dispersion compensation amount can be set. Figure 17 shows a configuration where the variable dispersion compensator is installed in the transmitter, the receiver, and in every repeater. In a system where a plurality of dispersion compensators are installed, all the compensators need not necessarily be of dispersion variable type but some may be constructed from fixed-type dispersion compensators. A fixed-type dispersion compensator can be implemented using a dispersion compensating fiber (DCF).

The dispersion compensation amount can be controlled by the variable dispersion compensator while monitoring the transmission characteristic not only when the system is started up but also while the system is in operation. In this way, proper control can be performed independently of the variation of the wavelength of the light source LD and the variation of the zero dispersion wavelength of the transmission line due to temperature changes and aging.

This process may be performed manually or may be automatically performed by the CPU. Furthermore, a separate CPU may be provided for each of the regenerative repeater sections between the optical transmitter and receiver for

independent control, or alternatively, control may be performed centrally by a single CPU while adjusting the relationships among the plurality of regenerative repeater sections.

Figures 18 and 19 show a yet further example. In this example, the variable dispersion compensator is used in conjunction with a tunable light source 106. Figure 18 shows a configuration for a repeaterless transmission system, and Figure 19 a configuration for an optical amplification multiple repeater transmission system. The invention, however, is not limited to the illustrated configuration where the variable dispersion compensator is installed in the transmitter, the receiver, and in every repeater, but various combinations are possible as mentioned with reference to Figure 14.

In this optical transmission system, the variable dispersion compensator is used in conjunction with the tunable light source 106 in the transmitter, and while measuring the transmission characteristic at the receiver, the transmission wavelength is swept and set to a value at which good transmission characteristic is obtained, or based on the transmission characteristic measured at the receiver, a control signal is fed back to the transmitter so that the wavelength of the tunable light source 106 is set to the optimum value.

As previously described, when transmission (both repeaterless transmission and multiple repeater transmission) is performed at a relatively high optical power level using an optical amplifier, if the wavelength of signal light is set near the zero dispersion wavelength of the optical-fiber transmission line and in an abnormal (positive) dispersion region, modulation instability occurs due to a four-wave mixing (FWM) phenomenon that occurs between the signal light and the amplified spontaneous emission (ASE). As a result, the ASE is amplified and the S/N ratio of the signal light degrades. It is known that this can be effectively avoided by setting the signal light wavelength within the normal (negative) dispersion region or by applying positive dispersion at the receiver or at the repeater. That is, dispersion compensation is performed by setting the wavelength of the tunable light source to a value that makes the dispersion value negative with respect to the transmission line and that can suppress FWM, while at the same time, setting the dispersion amount of the dispersion compensator to a positive value.

Alternatively, dispersion compensation may be performed by setting the wavelength of the tunable light source to a value that makes the dispersion value positive with respect to the transmission line and that can suppress FWM, while at the same time, setting the dispersion amount of the dispersion compensator to a negative value. The setting of the transmission wavelength may be done automatically. Also, the setting of the transmitting wavelength may be done when the system is started up, or while the system is in operation.

If there is a spare line whose dispersion condition and installation environment are approximately equal to those of the operating line, it will be possible to first optimize the dispersion compensation amount and transmission wavelength on the spare line and then apply the optimization to the operating line by reference to them. This enables the optimization of the respective quantities to be done without affecting the service speed.

Parameters for controlling the conditions of the transmission line may also include the prechirping amount and the optical power to be input to the fiber in addition to the signal light wavelength (Figures 1, 3, 4, 8, 9, 18, 19) and dispersion compensation amount (Figures 10 to 19) already described.

Prechirping is a technique for controlling the change of the transmitted waveform due to wavelength dispersion and nonlinear effects by preproviding a wavelength (frequency) distribution within one pulse of the transmission wavelength, and various methods have been proposed for implementation. When a Mach-Zehnder optical modulator is used as an external modulator, the relationship between applied voltage and optical power will be represented by a sine curve as shown in Figure 20. When a voltage near V_{b1} is selected and applied as a positive pulse, such as shown in part (1)(a) of Figure 21, a positive light pulse in phase with the applied voltage is output, as shown in part (2)(a) of Figure 21. At this time, the light wavelength shifts to the shorter value in the rising portion of the light pulse, and to the longer value in the falling portion, as shown in part (3)(a) of Figure 21. That is, within the duration of one light pulse, the wavelength shifts with time from the shorter wavelength (blue) to the longer wavelength (red). This phenomenon is called a red shift. On the other hand, when a voltage near V_{b2} is selected and applied as a negative pulse, such as shown in part (1)(b) of Figure 21, a positive pulse 180° out of phase with the applied voltage is output, as shown in part (2)(b) of Figure 21. At this time, the light wavelength shifts to the longer value in the rising portion of the light pulse, and to the shorter value in the falling portion, as shown in part (3)(b) of Figure 21. That is, within the duration of one light pulse, the wavelength shifts with time from the longer wavelength (red) to the shorter wavelength (blue). This phenomenon is called a blue shift. When a parameter defining the chirping amount is denoted by α , then $\alpha > 0$ for the red shift and $\alpha < 0$ for the blue shift. When the wavelength of the signal light is shorter than the zero dispersion wavelength and the transmission condition of the optical fiber is within the region of the normal dispersion ($D < 0$), light at longer wavelength travels through the optical fiber faster than light at shorter wavelength; therefore, if a pre-chirping of $\alpha > 0$ (red shift) is given in advance, this has the effect of compressing the pulse waveform, and suppresses waveform degradation. Conversely, when the transmission condition is within the region of the abnormal dispersion ($D > 0$), light at shorter wavelength travels faster, so that a prechirping of $\alpha < 0$ (blue shift) will serve to suppress waveform degradation. Further, by adjusting the value of α according to the condition of the transmission line, the overall transmission condition of the optical system can be optimized. In a Mach-Zehnder optical modulator, the sign of α can be changed between positive and negative depending on which operating point, V_{b1} or V_{b2} , is used. When a Mach-Zehnder optical modulator is used that consists of a intensity modulator 107 and a phase modulator 108 connected in tandem as shown in Figure 22, the prechirping amount

α can be varied continuously by varying the voltage being applied to the phase modulator 108. In the illustrated example, the intensity modulator and the phase modulator are integrated as a single device, but these may be constructed as separate devices that are connected together.

As for the input optical power to the fiber, by varying the transmitter optical power and the repeater optical output power, the waveform change due to the interaction between self-phase modulation and chromatic dispersion in the transmission line can be regulated. In the case of WDM transmission, the amount of crosstalk (described later) due to FWM can also be changed by varying the optical power. Varying the optical power can be easily accomplished by controlling the optical output powers of the transmitting light source and of the optical amplifiers (optical post-amplifier and in-line optical amplifier).

Control of the prechirping amount and/or control of the optical power can be performed in place of or in conjunction with control of the signal light wavelength and/or control of the dispersion compensation amount, in the examples previously shown in Figures 1, 3, 4, 8 to 19.

In the examples thus far described, the transmission characteristic is measured periodically or continuously, and the control parameters, such as the signal light wavelength, etc., are adjusted in such a manner as to compensate for the change of the zero dispersion wavelength λ_0 in the transmission line. One of factors that change the zero dispersion wavelength λ_0 is a temperature change in the transmission line. Regarding the temperature change, the transmission conditions can also be optimized by estimating the amount of shift of the zero dispersion wavelength by evaluating the temperature of the transmission line, and by correcting the control parameters based on the estimated shift amount.

Further, in an optical amplification multiple repeater WDM system using a wavelength band near the zero dispersion wavelength of the optical fiber, crosstalk caused by four-wave mixing between signal lights becomes a factor that can degrade the transmission characteristic. To avoid this crosstalk, the signal wavelength band must be spaced far away from the zero dispersion wavelength of the transmission line, contrary to the case of one-wave transmission. An example of the spacing of signal light wavelengths is shown in Figure 23. In this case also, it is important to assess the variation of λ_0 along the longitudinal direction of the actual optical-fiber transmission line.

Figure 24 shows the temperature dependence of λ_0 actually measured.

Source: H. Onaka et al., "Measuring the Longitudinal Distribution of Four-Wave Mixing Efficiency in Dispersion-Shifted Fibers," IEEE Photonics Technology Letters, Vol. 6, No. 12, 1994.

In this example, for a DSF of 1.1 km length, λ_0 is obtained from the occurrence efficiency of four-wave mixing (FWM). Here, a change of 2.4 nm (rate of change: 0.03 nm/°C) is shown over a temperature range of -20 to +60°C. Since the dispersion slope of the DSF used here is 0.07 ps/nm²/km, the wavelength dispersion value changes at a rate of 0.168 ps/nm/km. At transmission speeds 10 Gb/s or over, this change may have to be taken into consideration in system design together with the variation along the longitudinal direction.

Temperature is evaluated at an appropriate point 110 on the optical-fiber transmission line 102 installed between the optical transmitter 100 and the optical receiver 103, as shown in Figure 25, or at multiple points as shown in Figure 26. When temperature is evaluated at multiple points, the distribution of shift amounts of the zero dispersion wavelength can be obtained. In the case of an optical amplification repeater transmission system, temperature is evaluated at one point or at multiple points on every repeater section 102 or on some of the repeater sections.

Temperature evaluation can be accomplished by directly measuring the temperature of the fiber-optic cable of the transmission line using a suitable temperature sensor, or the temperature of the fiber-optic cable can be estimated by measuring the tube temperature, or in the case of an underground optical-fiber cable, by measuring the temperature of the earth surface under which the cable is buried, or in the case of an undersea cable, by measuring the water temperature. Furthermore, the cable temperature can be estimated from the ambient temperature at an end station or at a repeater, or from the temperature of the earth surface. A continuous temperature distribution can be measured by laying an optical fiber for temperature measurement along the fiber-optic cable and by using OTDR (Optical Time Domain Reflectometry) in order to measure Raman scattered light.

From the temperature evaluation value thus obtained, the amount of variation of λ_0 is computed and based on which, control parameters such as signal light wavelength are corrected. It is also possible to create calendars for average seasonal and day-to-night variations from the past temperature evaluation results and change the control parameters using such calendars (or data may be preprogrammed).

Figures 28 and 29 are concerned with an example in which signal light wavelength is corrected for each regenerative repeater section for optimum transmission conditions by controlling the tunable light source 106 based on the temperature evaluation value. Figure 28 shows an example of a repeaterless transmission system, and Figure 29 an example of an optical amplification repeater transmission system. Figure 30 is concerned with an example where the prechirping amount α is corrected based on the temperature evaluation value.

Figures 31 to 33 are concerned with an example where the dispersion compensation amount is corrected. An optical amplification repeater transmission system is shown here, but it will be recognized that the example is also applicable to a repeaterless transmission system. Figure 31 shows a configuration where the variable dispersion compensator 101 is installed in the transmitter, Figure 32 concerns a configuration where the variable dispersion compensator 101 is

installed in the receiver, and Figure 33 illustrates a configuration where the variable dispersion compensator 101 is installed in both the transmitter and receiver, and also in every repeater.

Figure 34 is concerned with an example in which the waveform degradation due to the SPM-GVD effect is suppressed by correcting transmitter power and repeater optical output power based on the temperature evaluation value. Instead of controlling the amplifier, the light source may be controlled. Figure 35 is concerned with an example where signal light wavelength, prechirping amount, dispersion compensation amount, and optical power are corrected.

The processing for these corrections may be performed manually or may be automatically performed by the CPU. Furthermore, a separate CPU may be provided for each of the regenerative repeater sections between the optical transmitter and receiver for independent control, or alternatively, control may be performed centrally by a single CPU while adjusting the relationships among the plurality of regenerative repeater sections.

It is believed that the SPM effect is caused by abrupt changes in fiber refractive index due to abrupt changes in light intensity. Therefore, by transmitting optical pulses with the rise time and fall time forcefully stretched and thereby smoothing the variation of optical signal strength, the waveform degradation due to the SPM effect can be reduced. In this case, rather than causing only the light intensity to vary smoothly and stretching the rising/falling transition times, it would be preferable to stretch the transition times by deliberately causing wavelength dispersion, since it would then be possible to compensate for it by dispersion compensation or other means in a later stage. Deliberate wavelength dispersion can be caused either by intentionally shifting the signal light wavelength from the zero dispersion wavelength λ_0 and thereby causing dispersion by GVD, or by inserting a dispersion compensator in the transmitter.

Figures 36 and 37 are concerned with an example in which the wavelength λ_s of signal light is set to a value spaced apart from the zero dispersion wavelength λ_0 of DSF and a dispersion compensator 112 with a fixed dispersion amount is installed at the receiving end. Figure 36 shows an example of repeaterless transmission, and Figure 37 an example of multiple repeater transmission. The dispersion amount D of the dispersion compensator 112 is set to a value that can compensate for the GVD caused by

Figures 38 and 39 are concerned with an example where the dispersion compensator 112 is installed at the transmitting end. Figure 38 shows an example of repeaterless transmission, and Figure 39 an example of multiple repeater transmission. In this case also, the dispersion amount D of the dispersion compensator 112 is set to a value that can compensate for the GVD caused by

In the example of Figure 36 or 37, if the system is set expressly for $\lambda_s < \lambda_0$ and $D > 0$, as shown in Figure 40, since λ_s is in the negative dispersion region, four-wave mixing between signal light and spontaneous emission can be prevented. Of course, a combination of $\lambda_s > \lambda_0$ and $D < 0$, as shown in Figure 41, can also serve the purpose. Furthermore, dispersion compensators with dispersion value D of opposite signs may be installed at the transmitter and receiver, respectively, as shown in part (a) and part (b) of Figure 42. It is also possible to install a dispersion compensator at the transmitter, at the receiver, and at every repeater or some of the repeaters as shown in Figure 43.

Further optimization can be achieved by measuring the transmission characteristic with the wavelength λ_s of signal light first set at a value spaced apart from the zero dispersion wavelength λ_0 and with the dispersion compensator arranged at an appropriate location to suppress the SPM effect, as described above, and then by correcting λ_s to an optimum value based on the result of the measurement. Figures 44 and 46 show several examples of such a system configuration. For the method of measuring the transmission characteristic and the mode of control, any of the various methods and modes already described can be applied. As shown in Figures 47 to 49, the prechirping amount may be controlled with the signal light wavelength λ_s fixed. Alternatively, both the signal light wavelength λ_s and the prechirping amount may be controlled, as shown in Figures 50 to 52. Control of the prechirping amount can be accomplished using a Mach-Zehnder optical modulator, as previously described.

In the examples thus far described, a single signal light wavelength was used throughout one regenerative repeater section between the optical transmitter and receiver, regardless of the provision of an optical amplification repeater. In the examples hereinafter described, a wavelength converter is installed in every optical amplification repeater and the signal light wavelength λ_s is optimized for each amplification repeater section.

Figure 53 shows an example of an optical transmission system in which a wavelength converter 118 is provided in every optical amplification repeater and the signal light wavelength is optimized for each amplification repeater section. In the example of Figure 53, the wavelength converter 118 is provided for every amplification repeater section, but the invention is not limited to this configuration. Furthermore, a variable wavelength light source 106 may be provided in the transmitter, as shown in Figure 54, to further optimize the signal light wavelength for the section between the transmitter and the first optical amplification repeater.

The wavelength converter 118 can be implemented using a wavelength converting laser constructed, for example, from a bistable optical laser such as shown in Figure 55. The left-hand half of the figure is the region of optical bistability; the electrode above the active layer 120 is divided into two sections, and the portion between them is used as a saturable absorption region. When input light is injected while the device is held in a state about to oscillate by adjusting currents in gain regions 122 and 124, the saturable absorption region 126 becomes transparent and starts lasing, producing output lights at different wavelengths. The right-hand half of the figure is the control region for oscillation wavelength, which consists of a phase shift region 128 and a DBR region 130 having a diffraction grating 129. When current is

injected into the DBR region 130, the refractive index of a light guide layer 132 decreases because of the plasma effect caused by carriers, thus making it possible to shift the Bragg wavelength toward the shorter wavelength side. Further, by varying the current being injected to the phase shift region 128, an equivalent light path length of this region can be varied, which makes it possible to match the phase of light to the oscillation condition. Therefore, by suitably varying the currents applied to these two regions, the wavelength of output light can be controlled over a wide range.

In a second implementation of the wavelength converter 112, the phenomenon of four-wave mixing is deliberately made use of. When light at two wavelengths, λ_0 and λ_{in} , near the zero dispersion wavelength, is input to the DSF, light of λ_{out} is produced as a result of four-wave mixing. When a tunable light source is used to emit λ_0 which is made variable, and only light at λ_{out} is extracted from the output light by using a filter, λ_{in} can be converted to λ_{out} while controlling its wavelength.

By setting signal light wavelength for each optical amplification repeater section, it becomes possible to further increase the transmission speed, since wavelength dispersion can be further reduced, and the transmission line cost can be reduced since the allowable range for the variation of the zero dispersion wavelength λ_0 can be expanded. Furthermore, by wavelength-converting highspeed optical signals as light at each optical amplification repeater, rather than regenerating and repeating them and setting the signal light wavelength once again for further transmission, two conversions between optical and electrical signals and associated high-speed electronic circuitry can be omitted, thus achieving reductions in the size and cost of the system.

When the zero dispersion wavelength of the transmission line, including its variation along the longitudinal direction, is already known, the signal light wavelength is set at an optimum value for each optical amplification repeater section through simulation, etc. On the other hand, when the zero dispersion wavelength of the transmission line is not known, the transmission characteristic is measured at the receiving end when the system is started up, while sweeping the wavelength by the tunable light source and wavelength converter, and the wavelength is set for optimum transmission characteristic. It would also be possible to sweep the wavelength while feeding back the control signal from the transmission characteristic measuring section 105, as shown in Figure 56. In this case, each wavelength converter is first set to zero wavelength shift amount, and the tunable light source is operated to perform sweeping to determine the wavelength that provides the best transmission characteristic. If the transmission characteristic does not meet the specification at this time, then the wavelength converters could be operated to perform sweeping, for example, in sequence first starting with the wavelength converter closest to the transmitter, then the next closest one, and so on, setting each to the wavelength that provides the best transmission characteristic. For the method of measuring the transmission characteristic and the mode of control during system startup and during system operation, any of the various methods and modes already described can be applied.

In the example shown in Figure 57, a dispersion compensator 112 for deliberately causing GVD is provided in the transmitter to reduce the SPM effect as already described. The dispersion compensator may also be installed at each repeater.

Next, peripheral techniques for implementing optical multiplexing will be described.

The Mach-Zehnder optical modulator, used to produce an optical signal by modulating a light beam from a light source with an electrical signal, has a sinusoidal characteristic as previously described with reference to Figure 20, but since the characteristic drifts with changing temperature and aging, the drift must be compensated for so that the variation range (operating point) of the applied voltage is always held within specified limits. Japanese Patent Unexamined Publication No. 3-251815 discloses a technique whereby the drift of a Mach-Zehnder modulator is compensated for by amplitude-modulating the applied voltage (high-frequency electrical signal) with a low-frequency signal of frequency f_0 and by controlling the bias of the applied voltage so that the f_0 component contained in the output light becomes zero. That is, when the driving voltage range $V_0 - V_1$ is within the proper limits, the upper and lower envelopes of the output light signal vary with frequency $2f_0$, their phases being opposite from each other, as shown in Figure 58, so that no f_0 component is contained; on the other hand, when the operating point has shifted outside the proper range, the upper and lower envelopes of the output light signal vary with frequency f_0 and in phase with each other, as shown in Figures 59 and 60, so that the f_0 component is contained. To prevent this, part of the output light signal is separated using a coupler and converted to an electrical signal, and the bias of the optical modulator is controlled using an output phase-detected at f_0 , to stabilize the operating point.

When such a drift compensation technique is applied to an optical multiplexing system, since each optical channel requires the provision of an optical modulator, an equal number of drift compensation circuits need to be provided. Accordingly, if the above drift compensation technique is directly applied to an optical multiplexing system, there arises the problem that couplers for splitting optical signals and optical detectors for converting separated optical signals into electrical signals become necessary in large numbers.

Figure 61 shows an example of an optical multiplexing system equipped with a drift compensation circuit according to the present invention. In this example, laser beams of the same wavelength λ_0 are input to a plurality of Mach-Zehnder optical modulators, 201₁, 201₂, ..., arranged in parallel, and drive circuits, 203₁, 203₂, ..., for the optical modulators, 201₁, 201₂, ..., amplitude-modulate drive signals (modulation signals) with low-frequency signals of different frequencies f_1 , f_2 , ..., generated by low-frequency oscillators, 204₁, 204₂, ...

Output lights from the optical modulators, $201_1, 201_2, \dots$, are optically combined and transmitted onto an optical transmission line, while part of the combined light is separated as monitor light by using an optical coupler 205; the separated light is then converted to an electrical signal and further divided into a plurality of signals which are passed through band filters $208_1, 208_2, \dots$, and applied to corresponding phase-detection/bias-supply circuits $202_1, 202_2, \dots$. The band filter 208_k ($k = 1, 2, \dots$, the same applies hereinafter) transmits frequency f_k of the low-frequency-superimposed components of the corresponding optical modulator 210_k .

The phase-detection/bias-supply circuit 202_k phase-detects the low-frequency component of the output light extracted by the band filter 208_k with the output of the oscillator 204_k , and generates a signal to control the operating point of the optical modulator 201_k . This control is performed simultaneously in all the optical modulators $202_1, 201_2, \dots$

In the above configuration, the phase-detection/bias-supply circuit 202_1 for the optical modulator 201_1 is controlled using the low-frequency component f_1 extracted by the band filter 208_1 , and likewise, the phase-detection/bias-supply circuit 202_2 for the optical modulator 201_2 is controlled using the low-frequency component f_2 extracted by the band filter 208_2 . Accordingly, bias control for each of the optical modulators, $201_1, 201_2, \dots$, arranged in parallel, can be performed independently of each other.

The above configuration is effective when performing optical time-division multiplexing (OTDM) of a plurality of optical signals. By performing output light separation and optical/electrical conversion at one location, simultaneous control of a plurality of optical modulators can be accomplished. In this example, the band filters, $208_1, 208_2, \dots$, are used to extract the corresponding frequency components after optical/electrical conversion and separation, but if stable operation can be ensured, these filters may be omitted.

In the example of Figure 61, control of the operating point drift by low-frequency amplitude modulation is performed simultaneously in all the optical modulators, $201_1, 201_2, \dots$, operating in parallel. Alternatively, the system may be constructed in such a manner that each of the drive circuits for performing low-frequency amplitude modulation is switched into operation in turn at certain intervals of time so that at any given time only one drive circuit is performing low-frequency amplitude modulation; in that case, the operating point drift only of the optical modulator currently performing the low-frequency modulation is detected and controlled, while the operating points of the other optical modulators are held fixed. In this manner, signals of the same frequency can be used as the low-frequency signals.

Figure 62 shows an example of such an optical multiplexing system. In this example, control is switched, at fixed intervals of time T_0 , between optical modulators arranged in parallel. More specifically, a plurality of Mach-Zehnder optical modulators, $201_1, 201_2, \dots$, are arranged in parallel; first, optical signals of the same wavelength λ_0 are modulated by the optical modulators, $201_1, 201_2, \dots$, and then, the modulated signals are combined together. Only one low-frequency generator 204 is provided that generates a single low frequency f_0 which is supplied via a selector switch 209 to the drive circuits, $203_1, 203_2, \dots$, each of which is switched into operation in turn at fixed intervals of time T_0 . Each drive circuit thus switched into operation in turn at fixed time intervals performs low-frequency amplitude modulation with the single frequency f_0 .

On the output side of the optical modulators, $201_1, 201_2, \dots$, the combined output light is split by the optical coupler 205 and converted by the optical detector 206 into an electrical signal which is supplied to the phase-detection/bias-supply circuit 202. The phase-detection/bias-supply circuit 202 phase-detects the low-frequency component in the electrical signal converted from the separated output light with the low-frequency f_0 signal from the low-frequency oscillator 204, and generates a bias voltage for output.

The output of the phase-detection/bias-supply 202 is supplied via a selector switch 210 to the optical modulators $201_1, 201_2, \dots$. The selector switch 210, which operates in interlocking fashion with the selector switch 209, controls the operating point drift by supplying the bias voltage only to the optical modulator whose associated drive circuit is performing low-frequency amplitude modulation. During that time, the operating points of the other optical modulators are held fixed (for example, using a latch or the like: the same applies hereinafter).

This example, as with the example of Figure 61, is effective when optical time-division multiplexing a plurality of optical signals, and has an additional advantage that control can be accomplished using one phase-detection/bias supply-circuit. To prevent occurrence of drifts in the optical modulators not under control, the time T_0 is set as short as possible but sufficiently longer than the time constant of control.

Figure 63 shows another example of the optical multiplexing system of the invention. In this example, the optical modulators, $201_1, 201_2, \dots$, are arranged in series. That is, the system is constructed with a plurality of Mach-Zehnder optical modulators, $201_1, 201_2, \dots$, arranged in series so that the light of wavelength λ_0 from the light source undergoes modulation two or more times. This system should not be called an optical multiplexing system because optical signals are not multiplexed. In this specification, however, the system is called an optical multiplexing system, for convenience.

The drive circuits, $203_1, 203_2, \dots$, for the optical modulators, $201_1, 201_2, \dots$, are constructed to perform low-frequency amplitude modulation with respectively different frequencies f_1, f_2, \dots . The output light from the final-stage optical modulator is split by the optical coupler 205 and converted by the optical detector 206 into an electrical signal which is supplied to the phase-detection/bias-supply circuits, $202_1, 202_2, \dots$, via the respective band filters $208_1, 208_2, \dots$. The band filter 208_k transmits the frequency f_k of the low-frequency-superimposed components of the corresponding optical modulator 201_k .

The phase-detection/bias-supply circuit 202_k phase-detects the low-frequency component in the signal separated from the output light with the low-frequency f_k signal from the oscillator 204_k, and thus detects an operating point drift and controls the operating point of the corresponding optical modulator 201_k. Control of the operating point is performed simultaneously in all the optical modulators, 201₁, 201₂, ... If stable operation can be ensured, the band filters, 208₁, 208₂, ..., may be omitted.

In the example of Figure 63, control of the operating point drift using low-frequency superimposition is performed simultaneously in all the optical modulators, 201₁, 201₂, ... Alternatively, the system may be constructed in such a manner that each of the drive circuits for performing low-frequency amplitude modulation is switched into operation in turn at certain intervals of time so that at any given time only one drive circuit is performing low-frequency amplitude modulation; in that case, the operating point drift only of the optical modulator currently performing the low-frequency modulation is detected and controlled, while the operating points of the other optical modulators are held fixed.

Figure 64 shows an example of such an optical multiplexing system. In this example, control is switched, at fixed intervals of time T_0 , between optical modulators, 201₁, 201₂, ..., arranged in series. More specifically, a plurality of Mach-Zehnder optical modulators, 201₁, 201₂, ..., are arranged in series to construct a system in which light from the light source undergoes modulation two or more times. Only one low-frequency generator 204 is provided that generates a single low frequency f_0 which is supplied via the selector switch 209 to the drive circuits, 203₁, 203₂, ..., each of which is switched into operation in turn at fixed intervals of time T_0 . Each drive circuit thus switched into operation in turn at fixed time intervals performs low-frequency amplitude modulation with the single frequency f_0 .

The output light from the final-stage optical modulator is split by the optical coupler 205 and converted by the optical detector 206 into an electrical signal which is supplied to the phase-detection/bias-supply circuit 202. The phase-detection/bias-supply circuit 202 phase-detects the low-frequency component in the electrical signal converted from the separated output light with the single low-frequency f_0 signal from the low-frequency oscillator 204, and generates a bias voltage for output.

The output of the phase-detection/bias-supply 202 is supplied via the selector switch 210 to the optical modulators 201₁, 201₂, ... The selector switch 210, which operates in interlocking fashion with the selector switch 209, controls the operating point drift by supplying the bias voltage only to the optical modulator whose associated drive circuit is performing low-frequency amplitude modulation. During that time, the operating points of the other optical modulators are held fixed.

This example, as with the example of Figure 63, is effective for optical time-division multiplexing, and has an additional advantage that control can be accomplished using one phase-detection/bias-supply circuit.

Figure 65 shows another example of the optical multiplexing system of the invention. In this example, the optical modulators, 201₁, 201₂, ..., arranged in parallel, modulate lights of respectively different wavelengths, λ_1 , λ_2 , ..., which are then wavelength-multiplexed. The drive circuits, 203₁, 203₂, ..., for the optical modulators, 201₁, 201₂, ..., perform low-frequency amplitude modulation with respectively different frequencies f_1 , f_2 , ... That is, a plurality of Mach-Zehnder optical modulators, 201₁, 201₂, ..., are arranged in parallel to construct a system in which optical signals of different wavelengths, λ_1 , λ_2 , ..., are wavelength-multiplexed. The drive circuits, 203₁, 203₂, ..., for the optical modulators, 201₁, 201₂, ..., perform low-frequency amplitude modulation with respectively different frequencies f_1 , f_2 , ..., and the optical outputs from the optical modulators, 201₁, 201₂, ..., are combined together to produce wavelength-multiplexed output light.

The wavelength-multiplexed output light is split by the optical coupler 205 and converted by the optical detector 206 into an electrical signal which is supplied to the phase-detection/bias-supply circuits, 202₁, 202₂, ..., via the respective band filters 208₁, 208₂, ... The band filter 208_k transmits the frequency f_k of the low-frequency-superimposed components of the corresponding optical modulator 201_k. The phase-detection/bias-supply circuit 202_k phase-detects the low-frequency component in the signal split from the output light with the low-frequency f_k signal from the oscillator 204_k, and thus detects an operating point drift and controls the operating point of the optical modulator 201_k. This control is performed simultaneously in all the optical modulators, 201₁, 201₂, ...

This example is effective for wavelength multiplexing, and allows simultaneous control of a plurality of optical modulators, in the same principle as that of the example shown in Figure 61. If stable operation can be ensured, the band filters, 208₁, 208₂, ..., may be omitted.

In the example of Figure 65, control of the operating point drift using low-frequency amplitude modulation is performed simultaneously in all the optical modulators, 201₁, 201₂, ... Alternatively, the system may be constructed in such a manner that each of the drive circuits for performing low-frequency amplitude modulation is switched into operation in turn at certain intervals of time so that at any given time only one drive circuit is performing low-frequency amplitude modulation; in that case, the operating point drift only of the optical modulator currently performing the low-frequency modulation is detected and controlled, while the operating points of the other optical modulators are held fixed.

Figure 66 shows an example of such an optical multiplexing system. In this example, control is switched, at fixed intervals of time T_0 , between optical modulators, 201₁, 201₂, ..., arranged in parallel and to which optical signals of different wavelengths, λ_1 , λ_2 , ..., are input. More specifically, a plurality of Mach-Zehnder optical modulators, 201₁, 201₂, ..., are arranged in parallel; first, optical signals of different wavelengths λ_1 , λ_2 , ... are modulated by the respective optical

modulators, 201₁, 201₂, ..., and then, the modulated signals are combined together. Only one low-frequency generator 204 is provided that generates a single low frequency f_0 which is supplied via the selector switch 209 to the drive circuits, 203₁, 203₂, ..., each of which is switched into operation in turn at fixed intervals of time T_0 . Each drive circuit thus switched into operation in turn at fixed time intervals performs low-frequency amplitude modulation with the single frequency f_0 .

On the output side of the optical modulators, 201₁, 201₂, ..., the combined output light is split by the optical coupler 205 and converted by the optical detector 206 into an electrical signal which is supplied to the phase-detection/bias-supply circuit 202. The phase-detection/bias-supply circuit 202 phase-detects the low-frequency component in the electrical signal converted from the separated output light with the single low-frequency f_0 signal from the low-frequency oscillator 204, and generates a bias voltage for output.

The output of the phase-detection/bias-supply 202 is supplied via the selector switch 210 to the optical modulators 201₁, 201₂, ... The selector switch 210, which operates in interlocking fashion with the selector switch 209, controls the operating point drift by supplying the bias voltage only to the optical modulator whose associated drive circuit is performing low-frequency amplitude modulation. During that time, the operating points of the other optical modulators are held fixed.

This example, as with the example of Figure 65, is effective for wavelength multiplexing, and has an additional advantage that control can be accomplished using one phase-detection/bias-supply circuit.

Figure 67 shows another example of the optical multiplexing system according to the present invention. In this example, optical outputs from the optical modulators, 201₁, 201₂, ..., arranged in parallel and to which optical signals of different wavelengths λ_1 , λ_2 , ..., are input, are combined together to produce combined output light which is then separated by a wavelength separating device 212 into the signals of wavelengths, λ_1 , λ_2 , ..., as originally supplied from the optical modulators 201₁, 201₂, ..., before converting them to electrical signals. That is, a plurality of Mach-Zehnder optical modulators, 201₁, 201₂, ..., are arranged in parallel to construct a system in which optical signals of respectively different wavelengths, λ_1 , λ_2 , ..., are wavelength-multiplexed. Only one low-frequency oscillator 204 is provided that generates a single low frequency f_0 . The drive circuits, 203₁, 203₂, ..., perform low-frequency amplitude modulation with the single frequency f_0 .

Optical outputs from the optical modulators, 201₁, 201₂, ..., are combined together to produce wavelength-multiplexed output light. This wavelength-multiplexed output light is split by the optical coupler 205 and is passed through the wavelength separating device 212 for separation into the optical signals of wavelengths λ_1 , λ_2 , ... These separated optical signals are fed to the optical detectors, 206₁, 206₂, ..., for conversion into electrical signals which are supplied to the phase-detection/bias-supply circuits 202₁, 202₂, ..., respectively. The phase-detection/bias-supply circuits 202_k phase-detects the low-frequency component in the wavelength-separated signal with the low-frequency f_0 signal, and thus detects an operating point drift and controls the operating point of the corresponding optical modulator 201_k. This control is performed simultaneously in all the optical modulators 201₁, 201₂, ... This example, as with the example of Figure 65, is effective for wavelength multiplexing, and is particularly applicable where light wavelength provides better separability.

Figure 68 shows another example of the optical multiplexing system according to the present invention. In this example, control is switched, at fixed intervals of time T_0 , between optical modulators, 201₁, 201₂, ..., arranged in parallel and to which lights of different wavelengths, λ_1 , λ_2 , ..., are input, and using a tunable filter 213 whose transmission wavelength varies with time, the wavelength component only of the optical modulator currently under control is extracted.

More specifically, a plurality of Mach-Zehnder optical modulators, 201₁, 201₂, ..., are arranged in parallel to construct a system in which optical signals of different wavelengths, λ_1 , λ_2 , ..., are wavelength-multiplexed. Only one low-frequency oscillator 204 is provided that generates a single low frequency f_0 . The drive circuits, 203₁, 203₂, ..., perform low-frequency amplitude modulation with the signal frequency f_0 .

Optical outputs from the optical modulators, 201₁, 201₂, ..., are combined together to produce wavelength-multiplexed output light. This wavelength-multiplexed output light is split by the optical coupler 205, passed through the tunable optical filter 213, and converted by the optical detector 206 into an electrical signal. The tunable optical filter 213 is a filter whose transmission wavelength varies with time, and at any given time, extracts only one wavelength component for output. An output signal from the optical detector 206 is supplied via a selector switch 214 to phase-detection/bias-supply circuits, 202₁, 202₂, ..., each of which is switched into operation in turn at fixed intervals of time. The selector switch 214 operates in interlocking fashion with the tunable optical filter 213 so that when the tunable optical filter 213 is switched so as to transmit wavelength λ_k , the selector switch 214 is set so as to supply its output signal to the phase-detection/bias supply circuit 202_k.

The phase-detection/bias-supply circuit 202_k phase-detects the low-frequency component in the optical/electrical converted signal with the low-frequency f_0 signal, and detects and controls the operating point drift of the optical modulator 201_k corresponding to the extracted wavelength λ_k . During that time, the operating points of the other optical modulators are held fixed.

This example, as with the example of Figure 65, is effective for wavelength multiplexing, and is particularly applicable where wavelength selection using a tunable optical filter is easier than using other means. In this example, the drive circuits for performing low-frequency modulation need not be switched in sequence at fixed time intervals, but such

switching may be performed to ensure clear separation of the low-frequency component appearing as a result of the operating point drift of each optical modulator.

Figure 69 shows another example of the optical multiplexing system according to the present invention. The optical multiplexing system shown here is constructed by adding sign-inverting circuits 215_k and 216_k, described in Japanese Unexamined Patent Publication No. 4-140712, to the system shown in Figure 61. As described with reference to Figures 20 and 21, in the Mach-Zehnder optical modulator the direction of prechirping can be changed from red shift to blue shift by changing the operating point from Vb1 to Vb2. When the wavelength of the signal light is in the normal dispersion region of the DSF, red shift is provided, and when it is in the abnormal dispersion region, blue shift is provided, to improve the waveform. The sign-inverting circuit 215_k changes the operating point from Vb1 to Vb2 by inverting, in accordance with an operating point switching signal, the polarity of the low-frequency signal being applied from the oscillator 204_k to the drive circuit 203_k. When the operating point is changed to Vb2, the logic of the optical signal are reversed, so that the logic of the modulation signal is inverted by the sign-inverting circuit 216_k in synchronism with the switching operation of the sign-inverting circuit 215_k. Instead of inverting the logic of the signal supplied from the oscillator 204_k to the drive circuit 203_k, the logic of the signal supplied from the oscillator 204_k to the phase-detection/bias-supply circuit 202_k, or the result of phase detection in the phase-detection/bias-supply circuit 202_k, may be inverted. Furthermore, the switching of the operating point may be performed simultaneously for all the optical modulators 201_k.

In the example of Figure 69, sign-inverting circuits are added to the optical multiplexing system of Figure 61, but the invention is not limited to this particular example. Rather, it will be appreciated that the sign-inverting circuits can be added likewise to any of the optical multiplexing systems thus far described (Figures 62 to 68), in which case the switching operation of the sign-inverting circuits may be performed individually or together in interlocking fashion.

Changing the operating point by the sign-inverting circuit (operating-point shift circuit) can be implemented in several ways; for example, an external selector switch may be provided, or automatic switching may be performed in the system by checking the transmission characteristic, for example, at the receiving end. When transmitting at a wavelength near the zero dispersion wavelength of the fiber, the sign of wavelength dispersion during transmission can become positive or negative, depending on the variation of the zero dispersion wavelength of the fiber, the variation of the light source wavelength, etc. In such cases, it may be useful if the operating point in each optical modulator is changed independently. In the case of wavelength multiplexing, when the relationship of magnitude between the zero dispersion wavelength of the fiber and each signal light wavelength is already known, it may be useful if the operating points in the optical modulators having the same relationship of magnitude are changed together at a time. In the case of optical time-division multiplexing also, the chirping of the output light wavelength can be reversed by changing the operating points of the serially arranged optical modulators at the same time.

Next, a clock extraction technique in optical time-division multiplexing (OTDM) will be described.

Figure 70 shows an optical time-division multiplexing transmission system in which the clock signal extraction according to the invention is applied. This embodiment is concerned with a system configuration that achieves a transmission rate of 40 Gb/s by two-wave multiplexing. Figure 71 is a timing chart for various signals used in the receiver of this system, showing the waveforms of the signals designated by reference signs, a to i, in Figure 70.

First, using a one-input, two-output optical switch 241 that operates on a single 20-GHz sine wave b, 20-GHz optical signals, c and d, whose phases are opposite from each other, are created from an optical signal, a, output from a light source LD (laser diode) 240. The optical clock signals, c and d, are then applied to external modulators 244 and 245, respectively, where they are externally modulated by 20-Gb/s NRZ signals, e and f, producing 20-Gb/s RZ optical signals g and h. Then, these signals are bit-multiplexed (optical MUX) by a wave combiner 246 which outputs a 40-Gb/s optical multiplexed signal i. With this optical time-division multiplexing (OTDM) method, 40-Gb/s optical transmission can be achieved without requiring an ultra-wideband electronic device capable of 40 Gb/s.

In an alternative configuration, a short-pulse light source or an LD with a semiconductor optical modulator may be used instead of the light source LD 240 and optical switch 241 shown in Figure 70, or the beam splitting optical switch 241 at the transmitting end may be replaced by a simple optical power splitting device or an external modulator which is driven by a sine wave.

At the receiving end, on the other hand, the 40-Gb/s optical multiplexed signal, i, must be demultiplexed into two 20-Gb/s RZ optical signal (optical DEMUX). Recent years have seen many proposals and experiments on optical DEMUX techniques using ultra-fast PLLs utilizing nonlinear effects such as four-wave mixing and cross-phase modulation (XPM), but any of the proposed techniques requires large-scale circuitry and furthermore, there are stability problems yet to be overcome.

The simplest method that can be considered is therefore by performing bit-demultiplexing alternately on a bit-by-bit basis using a one-input, two-output optical switch such as the one used in the transmitter shown in Figure 70. In Figure 70, the optical multiplexed signal received from the transmission line 248 is input to a bit-demultiplexing optical switch 252 via an optical preamplifier 249, while part of it is separated by an optical coupler 250 and input to a clock extraction circuit 251. In the clock extraction circuit 251, as shown in Figure 82 for example, the input signal is first converted to electrical form by an optical detector 260, and then a clock signal is directly extracted using a narrowband electrical filter (dielectric resonance filter, SAW filter, etc.) 262. The extracted clock signal is applied to the optical switch 252 as a signal

for providing bit-demultiplexing timing. In synchronism with this clock signal, the optical switch 252 demultiplexes the received 40-Gb/s optical multiplexed signal, i, into two 20-Gb/s RZ optical signals (optical DEMUX) and supplies them to respective optical receivers 253 and 254.

In this receiver configuration, however, a 20-GHz clock signal synchronized to the data main signal is required not only for the identification of the sign but for the optical switching operation of the optical switch 252; therefore, the received optical multiplexed signal needs to contain a 20-GHz component.

In the present invention, a 20-GHz component of a magnitude sufficient for the extraction of the clock signal is carried on the transmitted optical multiplexed signal, i, in the following way. That is, as shown in Figure 72, at the transmitter the two RZ signals, g and h, are generated with different amplitudes, and the clock signal is extracted from the resulting 40-GHz optical multiplexed signal i. As shown, the optical multiplexed signal, i, thus produced carries a 20-GHz clock signal component of sufficient magnitude as shown by a dotted line in the figure.

The following describes various methods for providing the optical signals with different amplitudes which are multiplexed to produce an optical multiplexed signal containing a clock signal component. For convenience of explanation, the following description deals with two cases: case A where separate light source LDs are used whose optical outputs are first modulated externally and then combined together, and case B where output light from one light source LD is split and the resulting signals are combined after external modulation, as in the example of Figure 70.

Figure 74 shows one example of case A. Separate light source LDs are provided that supply respective optical signals to external modulators 244 and 245; if these light source LDs, 240a and 240b, are set to different output powers, the optical signals, g and h, to be multiplexed can be provided with different amplitudes.

Figure 75 shows another example of case A. As shown, by inserting an optical attenuator 256 in one or other of the light paths leading from the light source LDs to the wave combiner 246, the optical signals, g and h, to be multiplexed can be provided with different amplitudes. In the illustrated example, the optical attenuator 256 is inserted between the external modulator 244 and the wave combiner 246, but it may be inserted between the light source LD 240a and the external modulator 244. Of course, the optical attenuator 256 may be inserted in the light path where the external modulator 245 is located. It would be possible to use an optical amplifier instead of the optical attenuator 256. Furthermore, these methods are applicable not only to external modulation but also to LD direct modulation or direct modulation using a modulator-incorporated LD.

Figure 76 shows an example in which the method of Figure 75 is applied to case B. This example of case B is identical to the foregoing example, except that only one light source LD is used, and therefore, detailed explanation is not given here.

In either case A or B, in an optical time-division multiplexing transmission system using external modulation, light intensity amplitude differences between a plurality of optical signals can be realized by using external modulators, 244 and 245, having different insertion losses.

When a Mach-Zehnder optical modulator is used as the external modulator, the amplitude of the output light can be changed by changing the amplitude of the voltage for driving the optical modulator or by changing its bias point. Figures 77 and 78 are diagrams for explaining how this can be achieved. Figure 77 shows how the light output strength changes when the amplitude value of the drive voltage (applied voltage) is changed from V_e to V_f . Figure 78 shows how the light output intensity changes when the bias voltage of the drive voltage is changed from V_{B-e} to V_{B-f} . In this way, as long as a Mach-Zehnder light modulator is used for each external modulator, the output light intensities of the external modulators 244 and 245 can be changed by changing the drive voltage amplitude or the bias voltage.

Furthermore, in case B, it is also possible to provide the optical outputs of the external modulators with different amplitudes by setting the split ratio of the output light of the light source LD 240, in the optical switch 241 (or a passive optical power splitting device that can be used in its place), to a value other than 1:1.

Figure 79 shows another example of case B. In this example, the external modulators 244 and 245 are set so that their optical outputs are linearly polarized with their principal axes of polarization perpendicular to each other. When optical-multiplexing the two RZ signals having different polarization conditions, for example, with their principal axes of linear polarization at right angles to each other, as described above, if a polarization-dependent optical device 257 is inserted in a light path after the optical multiplexing in the transmitter (wave combiner 246), the multiplexed two optical signals will emerge from the optical device 257 with their amplitudes of light intensity different from each other, thus producing an optical multiplexed signal with its light amplitude varying between alternate bits.

Instead of inserting the polarization-dependent optical device 257 as described above, it would be possible to replace the wave combiner by a wave combiner whose combining ratio is dependent on polarization either structurally or by the incident polarization axes of the optical signals.

Furthermore, in a transmission system in which the polarization relationship between alternate bits at the transmitter is maintained to a certain degree through to the receiver, a polarization-dependent optical device 258 may be inserted before the optical demultiplexing in the optical switch 252 in the receiver, as shown in Figure 80.

This embodiment has described two-wave multiplexing having a difference in light intensity amplitude between alternate bits, but an N-wave multiplexing configuration is also possible. For example, in the case of a four-wave optical multiplexing transmission system also, a clock signal can be extracted from an optical multiplexed signal. Figure 73

shows an example of such four-wave multiplexing. When optical signals to be four-wave multiplexed are designated as g_1 , g_2 , g_3 , and g_4 , amplitude differences are set so that the relation holds. When these signals are combined to produce an optical multiplexed signal i , the optical multiplexed signal i will contain a clock signal component as shown by a dotted line in the figure. Further, in this example, it is possible to produce a multiplexed signal containing a plurality of clock signal components, depending on how the amplitude differences are set.

Another characteristic of the invention lies in the following point. That is, in conventional optical transmission systems at transmission rates up to 10 Gb/s, clock extraction is performed by splitting the main signal in the electrical stage after detecting (converting to electrical form) the signal light. By contrast, in the present invention, using one of the above-described methods a clock signal is extracted from the optical multiplexed signal separated from the main signal in the optical stage, and optical demultiplexing is performed using the thus extracted clock signal.

Another problem that arises in the multiplexing transmission system is that it is generally required that the correspondence between the channels at the transmitter before multiplexing and the channels at the receiver after demultiplexing be predetermined in fixed fashion. For example, in Figure 70, it is required that the signal supplied to the drive circuit 242 be always received by the optical receiver 253 and the signal supplied to the drive circuit 243 be always received by the optical receiver 254. However, in conventional OTDM transmission systems, since channel identification is not done at the receiver, the correspondence may change each time the system is started, making transmission line management impossible.

Figure 83 shows the configuration of an optical demultiplexer suitable for use at the receiving end of the OTDM communication system according to the present invention. The optical demultiplexer comprises an optical coupler 300 for splitting the received optical signal into two signals, a clock signal regenerating circuit 302 for regenerating a clock signal from one of the splitted signals, an optical switch 304 for separating the received optical signal as optical signal corresponding to each optical signal channel by using the regenerated clock signal, and two optical receivers, 306 and 308, each for recovering data from the optical signal on each separated channel. This configuration is fundamentally the same as that of the receiving section of the system shown in Figure 70.

Data on each optical signal channel is structured, for example, in the format shown in Figure 84. Data on each optical signal channel are optically multiplexed by bit-interleaving, and transmitted from the transmitter. In Figure 84, reference numeral 310 indicates frame synchronization data used to establish frame synchronization at the optical receiver 306 or 308, and 312 designates identification data for identifying the channel. Line identification data extraction circuits, 314 and 316, extract the identification data 312; in accordance with the identification data extracted by the line identification data extraction circuits 314 and 316, a control circuit 318 controls a signal switching circuit 320 to control the connection in the signal switching circuit 320 so that the data intended for an output line 1 is output onto the output line 1 and the data for an output line 2 is output onto the output line 2. Input signals to the line identification data extraction circuits 314 and 316 may be derived from the outputs of the signal switching circuit 320. The control circuit 318 is easily implemented using a microprocessor.

In the optical demultiplexer shown in Figure 85, instead of switching the output connection in each optical receiver the phase of the clock signal applied to the optical switch 304 is changed by controlling a phase shifter 322, thereby essentially achieving the same effect as connection switching. In the case of two-wave multiplexing, switching between the connections can be accomplished essentially by shifting the phase of the clock signal by 180° .

Figure 86 shows an example in which the optical demultiplexer of Figure 85 is expanded from the two-channel to the four-channel configuration. The clock signal reconstructed by the clock signal generating circuit 302 is supplied to the optical switch 304 via the phase changer 322. The clock signal is also supplied to a divide-by-2 frequency divider 303 where it is divided by 2, and the divided signal is then supplied to optical switches 305 and 305' via phase changers 323 and 323', respectively. Assuming that four-channel optical signals, CH1 to CH4, are multiplexed in the order of CH1, CH2, CH3, and CH4, as shown in part (a) of Figure 115, since the optical switch 304 is switched for each time slot by a clock signal shown in part (b) of Figure 115, CH1 and CH3 are output from one output as shown in part (c) of Figure 115 and CH2 and CH4 are output from the other output as shown in part (d) of Figure 115 in alternating fashion. Since the optical switches 305 and 305' are each switched for every two time slots by a clock signal shown in part (e) and part (h) of Figure 115, CH1 and CH3 are separated as shown in part (f) and (g) of Figure 115 and CH2 and CH4 are separated as shown in part (i) and part (j) of Figure 115, respectively. In accordance with the identification data extracted by the line identification data extraction circuits 314 to 317, the control circuit 318 controls the phase shifters 322, 323, and 323', for example, in such a manner that CH1 is output from output line 1, CH2 from output line 2, CH3 from output line 3, and CH4 from output line 4.

While the phase of the clock signal is shifted by 180° by the phase shifter 322 in Figure 85, in the optical demultiplexer shown in Figure 87 the optical signal before demultiplexing is delayed or advanced through an optical delay circuit 324 by the amount of time equivalent to a 180° phase shift of the clock signal. Instead of changing the phase of the clock signal, the same effect can be obtained by delaying or advancing the optical signal by the amount of time equivalent to it. The optical delay circuit 324 can be implemented using, for example, a corner cube 326, as shown in Figure 88, which is moved by mechanical means to change the light path length.

Figure 89 shows another example of the optical demultiplexer of the present invention. In the example of Figure 89, low-frequency signals, $f_1 - f_4$, of different frequencies for different channels, are superimposed, as shown in Figure 90, for channel identification, instead of using the identification data 312 in Figure 84. Figure 89 shows a case of two-wave multiplexing.

The optical signals separated by the optical switch 304 are split in the respective optical couplers 328 and 330, and converted by optical/electrical conversion circuits 332 and 334 into electrical signals which are supplied to low-frequency detectors 336 and 338 for detection of the low-frequency signals superimposed on the respective signals. The control circuit 318 identifies the channels from the frequencies of the low-frequency signals detected by the low-frequency detectors 336 and 338, and switches the connections in the signal switching circuit 320 so that the signals intended for the respective channels are output on the respective output lines 1 and 2. As described earlier, instead of switching the connections the phase of the clock signal may be changed as shown in Figure 91, or the optical signal may be delayed or advanced as shown in Figure 92. Further, in the case of two-wave multiplexing, since it is sufficient to identify one or the other of the two channels, the optical coupler 330, the optical/electrical conversion circuit 334, and the low-frequency detector 338 need not necessarily be provided, and only one channel may be used as shown in Figures 91 and 92. However, these circuits may be provided as spare circuits which are used in the event of failure of that one channel. Further, the optical receiver 306 or 308 may be provided with a light current monitor circuit 342 for monitoring the current flowing to an optical/electrical converting element 340, as shown in Figure 93, in which case the low-frequency signal can be derived from its output. In this case, the optical couplers, 328 and 330, and the optical/electrical conversion circuits, 332 and 334, can be eliminated.

Figure 94 shows the configuration of an optical transmitter for transmitting optical signals by superimposing thereon low-frequency signals f_i of different frequencies for different channels. Light from a light source 400 is "punched" in an external optical modulator 402 in synchronism with a clock signal, and optical pulse trains are produced, and split by an optical coupler 404 into a required number of outputs (two in the case shown in the figure). The first split light is modulated with a frequency f_1 in an external optical modulator 406, and further modulated with a first main signal in an external modulator 408. Likewise, the second split light is modulated with a frequency f_2 , and further modulated with a second main signal in an external optical modulator 412; the thus modulated light is passed through an optical delay element 414 to produce a time shift with respect to the first optical signal, and added together in an adder 416. Consequently, during the period (time slot) that the light is modulated with the first main signal, the frequency f_1 is superimposed in amplitude, and during the time slot in which the light is modulated with the second main signal, the frequency f_2 is superimposed in amplitude. It is desirable that the signal "punching" in the external optical modulator 402 be performed so that the resulting multiplexed signal will have the waveform shown in Figure 107, the pulse for each channel just occupying one time slot. The advantage obtained by this will be explained later.

In the optical multiplexing system shown in Figure 94, the input optical signal is split without introducing a phase difference between the split signals, and after applying modulation, a phase shift is introduced and the two signals are combined together; by contrast, in the optical multiplexing system shown in Figure 70, the input optical signal is split by the optical switch 241 into two signals with opposite phases, and these signals are directly combined together. In the latter system also, if an external optical modulator for modulating with the frequency f_1 or f_2 is provided in series to the external optical modulators 244 and 245, low-frequency signals of different frequencies for different channels can be superimposed. Each of the external optical modulators, 402, 406, 408, 410, and 412, can be implemented using a Mach-Zehnder optical modulator or an electric-field absorption optical modulator (EA optical modulator).

Figure 95 shows another example of the optical transmitter of the present invention. The number of external optical modulators can be reduced by already superimposing the frequencies f_1 and f_2 in amplitude on the respective main signals in drive circuits 418 and 420. The drive circuits 418 and 420 each can be implemented using a dual-gate FET such as shown in Figure 96. A waveform in drive circuits are shown in Figure 120.

The optical demultiplexer for the optical receiver explained with reference to Figure 83 to 91 can be modified to use it as a some kind of optical exchange that exchanges optical signals according to identification information included in an optical multiplexed signal. For example, by replacing the optical receiver 306 and 308 of Figure 85 and Figure 87 with optical couplers 600 and 602, respectively, as shown in Figure 116 and Figure 117, and by connecting another outputs of the optical couplers 600 and 602 to optical outputs 1 and 2, the modified optical demultiplexer can be used as an optical exchange. The circuit of Figure 91 or Figure 92 can be modified to an optical exchange by directly connecting the output of the optical couplers 328 and 330 to optical output line 1 and 2, as shown in Figure 118 or Figure 119.

When low-frequency signals are superimposed on the received signal, as shown in Figure 90, the low-frequency signals can be used not only for channel identification but also for control for stabilizing the phase of the clock signal used for optical demultiplexing. Figure 97 shows the configuration of an optical receiver having a phase controller for stabilizing the clock signal by using the superimposed low-frequency signals.

The optical receiver shown comprises an optical coupler 430 for splitting the received Q-bit optical signal into two signals, a timing regenerator 432 for regenerating a $Q/2$ -Hz clock signal from one of the split signals, an optical switch 434 for separating the optical signal as light into two $Q/2$ -bit/s optical signals by using the regenerated clock signal, and

optical receivers 436 and 438 for recovering the data signals from the separated optical signals. This configuration is fundamentally the same as that shown in Figure 83.

The phase of the clock signal supplied from the timing regenerator 432 to the optical switch 434 is changed by a phase shifter 439 which is under control of a phase controller 440. The phase controller 440 comprises an optical coupler 442 for splitting one of the separated Q/2-bit/s optical signals, an optical detector 444 for converting one of the separated optical signals into an electrical signal, a band-pass filter 446 for transmitting only a signal of designated frequency f_1 in the output from the optical detector 444, an oscillator 448 with an oscillation frequency of g_1 , a synchronous detection circuit 450 for performing phase synchronous detection on the output of the band-pass filter 446 with a signal of frequency g_1 , a comparator 452 for comparing the detection output of the synchronous detection circuit 450 with a predetermined reference value and for generating a control voltage based on the result of the comparison, and an adder 454 for adding the output of the comparator 452 to the output of the oscillator 448 and for outputting a control signal for the phase shifter 439. Low-frequency signals of different frequencies need not be superimposed on the optical signals of all channels, but need only be superimposed on a designated channel. In the latter case, the band-pass filter 446 can be eliminated. However, in the latter case also, if the band-pass filter 446 is inserted, the S/N ratio of the signal input to the synchronous detection circuit 450 can be improved.

It is assumed here that the frequency f_1 is superimposed only on CH1, as shown in Figure 98(a). When the phase of the clock signal perfectly matches the phase of the optical signal in the optical switch 434, as shown in Figure 98(b), the strength of the signal of frequency f_1 output from the optical detector 444 becomes the greatest, as shown in Figure 98(c). On the other hand, when the clock signal is out of phase, as shown in Figure 98(d), since the f_1 signal is not derived in its entirety in the optical switch 434, the strength of the f_1 signal decreases. More specifically, as the phase difference θ between the optical signal and the clock signal, as defined in Figure 99, changes from 0° to $\pm 180^\circ$, the strength of the f_1 component decreases linearly, as shown in Figure 100. Since the phase shifter 409 is controlled by the output of the oscillator 448, the clock signal is slightly phase-modulated with the frequency g_1 . Suppose here that the center of the phase variation is at point (b) in Figure 100. Then, since the strength of the f_1 component varies with the frequency g_1 and the straight line is upward to the right, the variation of the strength of the f_1 component is in phase or 180° out of phase with the frequency g_1 output from the oscillator 448. Therefore, when the phase synchronous detection is done in the synchronous detection circuit 450 with the frequency g_1 , the output takes a positive or negative value of the same magnitude. When the center of the phase variation is at point (c) in Figure 100, since the straight line is downward to the right, the phase detection output takes the same value as when at point (b) but the sign is inverted. When the center is at point (a), since half of the variation is folded back, there is no variation component of the frequency g_1 and the phase detection output becomes zero. Therefore, by comparing the output of the synchronous detection circuit 450 with the reference value, for example, the zero level, in the comparator 452, and by controlling the phase of the clock signal with the sum of the result of the comparison and the output of the oscillator 448, the operating point can be controlled to point (a) in Figure 100. The control signal being input to the comparator 452 is for inverting the polarity of the output of the comparator 452; when the polarity of the output of the comparator 452 is inverted, the center of the control shifts from point (a) (maximum) to minimum, thus shifting the phase, of the clock signal by 180° . Switching between the channels can be easily achieved in this manner.

The circuit shown in Figure 101 is a modified example of the optical receiver of Figure 97. In the circuit of Figure 101, not only the optical signal to the optical receiver 438 is split, but the optical signal to the optical receiver 436 is split by an optical coupler 460, and input to a phase controller 462 having the same configuration as the phase controller 440. However, while the center frequency of the band-pass filter in the phase controller 440 is f_1 , in the phase controller 462 the center frequency of the band-pass filter is f_2 to achieve locking on the other channel. The outputs of the band-pass filters in the phase controllers 440 and 462 are fed to a comparator 464 for comparison with a reference value. The enables the detection of any channel not in use. When one of the channels is not in use, a selector 466 is controlled to select the output signal of one or other of the phase controllers 440 and 462 and output it to control the phase of the clock signal using the phase shift amount control signal obtained for the channel in use. The phase shift amount control signal selected by the selector 466 is supplied to the phase shifter 439. If there is more than one channel identified as being in use, the selector 466 is controlled according to predetermined priority.

Figure 102 also shows a modified example of Figure 97. Instead of splitting the optical signal and converting it to an electrical signal for detection of low-frequency signals in the phase controller 440, the optical receiver 438 includes a light current monitor circuit 472 for an optical/electrical converting element 470, and low-frequency signals are derived from the output of the light current monitor circuit 472, as described with reference to Figure 93.

Figure 103 shows an example, of a configuration expanded to four-wave multiplexing. Two Q/2-bit/s optical signals separated by the optical switch 434 are further separated by optical switches 474 and 479 into four Q/4-bit/s optical signals. The Q/2-Hz clock signal output from the phase shifter 439 is divided by a divide-by-2 frequency divider 478, and the resulting Q/4-Hz clock signal is supplied to the optical switches 474 and 476 via phase shifters 480 and 482, respectively. The phase controller 440 controls the phase of the Q/2-Hz clock signal based on frequency f_1 . Since the frequency f_1 is superimposed, for example, on CH1 and CH3 time slots, as shown in Figure 104, the Q/2-Hz clock signal is phase synchronized to the CH1 or CH3 time slot under the control of the phase controller 440. This ensures stable

separation of CH1+CH3 and CH2+CH4 by the optical switch 434. It should be noted that f_1 need not necessarily be superimposed on CH3.

In the example of Figure 103, it is assumed that CH1+CH3 is input to the optical switch 476 and CH2+CH4 to the optical switch 474. A phase controller 484 controls the phase of the Q/4-Hz clock signal input to the optical switch 476, based on frequency f_2 . In the example shown in Figure 104, the frequency f_2 is superimposed on the CH1 time slot, so that the optical switch 476 can separate CH1 and CH3 stably. A phase controller 486 controls the phase of the Q/4-Hz clock signal input to the optical switch 474, based on frequency f_3 . In the example shown in Figure 104, the frequency f_3 is superimposed on the CH2 time slot, so that the optical switch 474 can separate CH2 and CH4 stably.

Figure 103 shows an example for four-wave multiplexing. A system for eight-wave or 16-wave multiplexing can be constructed by cascading an optical switch, divider, and phase controller in a similar manner.

In a modified example of the circuit of Figure 103, the phase shifters 480 and 482 and their associated phase controllers 484 and 486 can be omitted, as shown in Figure 105, provided that the phases of the optical path and electrical path are adjusted at the time of manufacture so that the phase of the Q/4-Hz clock signal applied to the optical switches 474 and 476 becomes optimum if the Q/2-Hz clock signal applied to the optical switch 434 is optimum. In this configuration, since only the low-frequency signal f_1 needs to be superimposed, the band-pass filter 446 also can be omitted.

Furthermore, the configuration of Figure 103 may be modified so that the frequencies, f_1 , f_2 , and f_3 , necessary for the phase controllers, 440, 484, and 486, can be detected from the output of the light current monitor circuit of the optical/electrical converting element provided in the optical receiver, as in the example shown in Figure 102. In this case, provisions must be made so that f_1 and f_2 are detected from the optical receiver 453 that is to receive CH1, and f_3 from the optical receiver 455 that is to receive CH3.

Figure 106 shows an example of the detailed configuration of the timing regenerator 432 and phase shifter 439 shown in Figures 97, 101, 102, 103, and 105. The timing regenerator 432 comprises an optical detector 490 for performing optical/electrical conversion, a nonlinear extraction circuit 492 for deriving a Q-Hz component from the output of the optical detector 490, a timing filter 494 for extracting only the Q-Hz component from the output of the nonlinear extraction circuit 492, a limiter amplifier 496 for keeping the output of the timing filter 494 at a constant amplitude, and a divide-by-2 frequency divider 498. It is advantageous to insert the phase shifter 439 between the timing filter 494 and the limiter amplifier 496.

Further, the nonlinear extraction circuit 492 comprises a differential circuit 500 and a full-wave rectification circuit 502. When signals with each pulse positioned within one time slot are optical multiplexed, the differential circuit 500 and full-wave rectification circuit 502 for performing nonlinear extraction can be omitted, thus simplifying the timing generator 432.

In the thus simplified configuration, the optical detector 490 for performing optical/electrical conversion may be constructed to have a resonant frequency at Q Hz as shown in Figure 108. This makes the fabrication of the optical detector easier, since the detector need not to have a flat frequency characteristic over a wide range. Furthermore, since the detector has a filter characteristic, the out-of-band attenuation characteristic of the timing filter 494 can be eased.

Figure 109 shows a modified example of the circuit of Figure 106. A coupler circuit 504 is used to separate a portion of a signal, and the level of the received signal is detected by a level detector 506. The detected level is compared in a comparator 508 with a reference value, and if the level is below the reference value, an input off alarm signal is output. Since the circuit from the input to the comparator 508 is made up only of passive components which are less prone to failure, the input-off condition of the light can be detected reliably. With this configuration, if a signal-off condition has occurred in the optical receiver, the cause of that condition can be identified, that is, whether the optical input signal has been cut off or has gone out of synchronization.

The optical switch for separating an input optical signal into two 180° out-of-phase optical signals by using a clock signal can be implemented by a directional active optical coupler using a Ti-diffused LiNbO₃ crystal waveguide described in Japanese Patent Unexamined Publication No. 55-7315. As shown in Figure 110, it can also be constructed using two gate-type optical switches 510 and 512, an optical coupler circuit 514 for distributing optical signals to them, and a phase shifter 516 for shifting the phase of the clock signal input to the gate-type optical switch 510 by 180°. This configuration can reduce polarization dependence than the directional active optical coupler. The gate-type optical switch is a device that exhibits varying transmittance with an applied voltage and therefore can also be used as an optical modulator. An electric-field absorption optical modulator (EA modulator) is an example.

In any of the optical receivers described with reference to Figures 97 to 105, an optimum clock signal was obtained by controlling the phase of the clock signal recovered from the received optical signal. Instead, it would be possible to generate a clock signal using a voltage-controlled oscillator (VCO) and control it so that the frequency and phase become optimum, as shown in Figure 111. In Figure 111, the phase controller 440 is identical in configuration and operation to the one shown in Figure 97. The clock signal supplied to the optical switch 434 is generated by the VCO 520, while the control signal output from the phase controller 440 is given to the VCO 520.

The following describes how the clock signal generated by the VCO 520 is controlled to the optimum value.

First, definitions are given as follows.

$\phi(t)$: Phase of the clock signal input to the optical switch 434 (phase of the output signal from the VCO 520)

$\alpha(t)$: Phase of the optical signal input to the optical switch (for simplicity, it is assumed that an alternating signal 1010 is input) with respect to channel 1

$\theta(t)$: $\phi(t) - \alpha(t)$ (see Figure 99)

ω_0 : Free-running angular frequency of VCO

$V(t)$: Control voltage for VCO x Angular frequency modulation sensitivity of VCO

V_o : Output value of synchronous detection circuit 450

K : Constant

The strength of the f_1 component that passes through the band-pass filter 446 (center frequency f_1) varies with the phase difference θ as shown in Figure 100.

Here, perturbation is applied to θ by adding a low-frequency signal, $I_0 \cos 2\pi g_1 t$, output from the oscillator 448, to the control voltage applied to VCO 520.

$$df/dt = \omega_0 + V(t) = \omega_0 + I_0 \cos 2\pi g_1 t + K V_o \quad (1)$$

Now, V_o is assumed to be changing slowly or in a steady state, and therefore constant.

Integrating equation (1) gives equation (2), from which it can be seen that ϕ is phase-modulated with the frequency g_1 .

$$f = (\omega_0 + K V_o)t + I_1 \sin 2\pi g_1 t + C \quad (C: \text{Constant of integration, } I_1: \text{Constant}) \quad (2)$$

Therefore, assuming that the derivative of $\alpha(t)$ with respect to time is constant, $\theta(t)$ is phase-modulated with the frequency g_1 as in the case of Figure 97.

When θ is phase-modulated, the f_1 component transmitted through the band-pass filter 446 exhibits the response shown in Figure 100, as already described. That is, at point (a) where the waveform is folded back, the component does not exist in the variation of the f_1 component. At point (b), it is in phase with the input signal, and at point (c), it is 180° out of phase.

Therefore, the output $V_o(t)$ of the synchronous detection performed using the output of oscillator 448, will be as shown in Figure 112.

(It is assumed that +1 is output when in phase and -1 when 180° out of phase.)

Next, the convergence of the operation is observed. When the perturbation component is removed for simplicity, this can be written as

$$df/dt = \omega_0 + V(t) = \omega_0 + K V_o(t) \quad (3)$$

Transforming this equation, we have

$$dq/dt = df/dt - da/dt = \omega_0 - da/dt + V_o(t) = D\omega_0 + K V_o(t)$$

Since $d\alpha/dt$ is a constant value, $d\omega_0/dt$ is a constant value. If K is positive and is large, and if $d\omega_0/dt > 0$, then when $\theta > 0$, $V_o(t) < 0$ and $dq/dt > 0$, and hence θ converges to 0, and when $\theta < 0$, $V_o(t) > 0$ and $dq/dt < 0$, and hence θ converges to 0.

From the above, it is shown that θ converges to 0, which indicates that the optical signal can be switched between the light paths by the optical switch with optimum timing.

Figure 113 shows a circuit configuration for implementing the detection of a light input-off condition in the receiver configuration shown in Figure 111. The received optical signal is split by an optical coupler 522 one of whose output is supplied to the optical switch 434 (Figure 111). The other output is supplied to an optical detector 524 for conversion into an electrical signal. This electrical signal is input to band-pass filters 526 and 528 for detection of the low-frequency components f_1 and f_2 , respectively, which are then normalized by being divided by a DC value in dividers 530 and 532, and are compared with a reference value in comparators 534 and 536, and the results of the comparisons are ANDed to produce an input off alarm signal. The circuit shown in Figure 111 assumes that f_1 is superimposed on one channel and f_2 on the other channel. Only one of f_1 and f_2 may be monitored, but when both are monitored, only one of the lines can be used. The dividers 530 and 532 are provided to remove the effects of input power variation, but these can be omitted when the input power is stable.

Figure 114 shows an expanded version of the circuit of Figure 111 for four-wave multiplexing. Clock signals applied to optical switches 540 and 542 are created by dividing the output of the VCO 520 by two in a divide-by-two frequency divider 544. The low-frequency signal f_1 is superimposed on CH1 and CH2.

Claims

1. An optical transmission system comprising:
 - an optical transmitter for generating an optical signal;
 - an optical transmission line for transmitting the optical signal generated by the optical transmitter;
 - an optical receiver for recognizing the optical signal transmitted over the optical transmission line; and
 - characteristic adjusting means for adjusting at least either a characteristic value of the optical signal or a characteristic value of the optical transmission line, and thereby matching the characteristic of the optical signal to that of the optical transmission line.
2. An optical transmission system according to claim 1, wherein the characteristic adjusting means includes a tunable light source whose emission wavelength is adjusted as the characteristic value of the optical signal to achieve the adjustment of the wavelength of the optical signal.
3. An optical transmission system according to claim 2, wherein the characteristic adjusting means includes a tunable filter installed at the receiving end of the optical transmission line and whose transmission wavelength is adjustable as the characteristic value of the optical transmission line according to the wavelength of the optical signal.
4. An optical transmission system according to claim 2 or 3, wherein
 - the optical transmission line comprises a plurality of optical fibers and an optical amplifier, installed between the optical fibers, for optically amplifying the optical signal transmitted through the optical fibers, and
 - the characteristic adjusting means includes a second tunable filter installed on an output side of the optical amplifier and whose transmission wavelength is adjustable as the characteristic value of the optical transmission line according to the wavelength of the optical signal.
5. An optical transmission system according to any one of claims 1 to 4, wherein
 - the optical transmission line includes optical fibers, and
 - the characteristic adjusting means includes a variable dispersion compensator, installed on the optical transmission line, for compensating for the wavelength dispersion characteristic of the optical fibers by adjusting a wavelength dispersion characteristic value of the optical transmission line as the characteristic value thereof.
6. An optical transmission system according to claim 5, wherein
 - the optical transmission line includes an optical amplifier, installed between the optical fibers, for amplifying the optical signal transmitted through the optical fibers, and
 - the wavelength of the optical signal is spaced apart from the zero dispersion wavelength of the optical fiber just enough to suppress four-wave mixing between spontaneous emission from the optical amplifier and the optical signal.
7. An optical transmission system according to any one of claims 1 to 5, wherein the characteristic adjusting means includes variable-chirping means for adjusting as the characteristic value of the optical signal the amount of prechirping to be given to the optical signal generated by the optical transmitter.
8. An optical transmission system according to claim 1, 2, 3, 4, 5, or 7, wherein
 - the optical transmission line includes an optical fiber, and
 - the characteristic adjusting means includes means for adjusting as the characteristic value of the optical signal the power of the optical signal entering the optical fiber.
9. An optical transmission system according to any one of claims 1 to 8, further including transmission characteristic measuring means for measuring a transmission characteristic by evaluating the quality of the optical signal recognized by the optical receiver, wherein
 - the characteristic adjusting means adjusts at least either the characteristic value of the optical signal or the characteristic value of the optical transmission line so that the transmission characteristic measured by the transmission characteristic measuring means is best adjusted.
10. An optical transmission system according to claim 9, further comprising characteristic value sweeping means for sweeping at least either the characteristic value of the optical signal or the characteristic value of the optical transmission line within a prescribed range, thereby making it possible to automatically find the best characteristic value.

11. An optical transmission system according to claim 9, wherein the transmission characteristic measuring means evaluates the quality of the optical signal by evaluating a bit-error rate in the optical signal.
- 5 12. An optical transmission system according to claim 9, wherein the transmission characteristic measuring means evaluates the quality of the optical signal by evaluating an eye pattern opening of the optical signal.
13. An optical transmission system according to claim 9, wherein the transmission characteristic measuring means evaluates the quality of the optical signal by evaluating a Q value of the optical signal.
- 10 14. An optical transmission system according to claim 9, wherein the transmission characteristic measuring means evaluates the quality of the optical signal by checking a parity bit in the optical signal.
- 15 15. An optical transmission system according to any one of claims 1 to 14, further comprising
an optical multiplexer for optically multiplexing a plurality of optical signals for output onto the optical trans-
mission line, and
an optical demultiplexer for optically demultiplexing a multiplexed optical signal transmitted over the optical
transmission line.
- 20 16. An optical transmission system according to any one of claims 10 to 15, wherein
the optical transmission line includes an operating channel and a spare channel, and
the characteristic value sweeping means performs the characteristic value sweeping on the spare channel.
- 25 17. An optical transmission system according to claim 1, further comprising temperature evaluating means for evaluating
the temperature of the optical transmission line in order for the characteristic adjusting means to adjust at least
either the characteristic value of the optical signal or the characteristic value of the optical transmission line according
to the change of the temperature of the optical transmission line.
- 30 18. An optical transmission system according to claim 17, wherein the temperature evaluating means evaluates the
temperature at a plurality of points along the optical transmission line.
- 35 19. An optical transmission system according to claim 17 or 18, wherein the temperature evaluating means measures
the temperature of the optical transmission line directly.
20. An optical transmission system according to claim 17 or 18, wherein the temperature evaluating means evaluates
the temperature of the optical transmission line by measuring temperature near the optical transmission line.
21. An optical transmission system according to claim 17 or 18, wherein the temperature evaluating means evaluates
the temperature of the optical transmission line by measuring temperature at a terminal or at a repeater.
- 40 22. An optical transmission system according to any one of claims 17 to 21, wherein the characteristic adjusting means
includes a tunable light source whose emission wavelength is adjusted as the characteristic value of the optical
signal to achieve the adjustment of the wavelength of the optical signal.
- 45 23. An optical transmission system according to any one of claims 17 to 22, wherein
the optical transmission line includes an optical fiber, and
the characteristic adjusting means includes a variable dispersion compensator, installed on the optical trans-
mission line, for compensating for the wavelength dispersion characteristic of the optical fiber by adjusting a wave-
length dispersion characteristic value of the optical transmission line as the characteristic value thereof.
- 50 24. An optical transmission system according to any one of claims 17 to 23, wherein the characteristic adjusting means
includes variable-chirping means for adjusting as the characteristic value of the optical signal the amount of prechirp-
ing to be given to the optical signal generated by the optical transmitter.
- 55 25. An optical transmission system according to any one of claims 17 to 24, wherein
the optical transmission line includes an optical fiber, and
the characteristic adjusting means includes means for adjusting as the characteristic value of the optical
signal the power of the optical signal entering the optical fiber.

26. An optical transmission system according to any one of claims 17 to 25, further comprising automatic adjusting means for automatically adjusting the characteristic adjusting means based on the evaluation value of the optical transmission line temperature given from the temperature evaluating means.

27. An optical transmission system comprising:

- an optical transmitter for generating an optical signal;
- an optical transmission line for transmitting the optical signal generated by the optical transmitter;
- an optical receiver for recognizing the optical signal transmitted over the optical transmission line; and
- means for reducing a nonlinear effect by smoothing variations of the strength of the optical signal transmitted through the optical transmission line.

28. An optical transmission system according to claim 27, wherein

the nonlinear effect reducing means includes means for providing the optical signal wavelength dispersion sufficient to reduce the nonlinear effect, and

the optical transmission system further comprises means for compensating for the wavelength dispersion caused by the wavelength dispersion providing means.

29. An optical transmission system according to claim 28, wherein

the wavelength dispersion providing means includes an optical fiber having a zero dispersion wavelength spaced apart from the wavelength of signal light just enough to give the optical signal wavelength dispersion sufficient to reduce the nonlinear effect, and

the wavelength dispersion compensating means includes a dispersion compensator.

30. An optical transmission system according to claim 29, wherein the optical fiber exhibits a negative dispersion value at the wavelength of the signal light.

31. An optical transmission system according to claim 29, wherein the optical fiber exhibits a positive dispersion value at the wavelength of the signal light.

32. An optical transmission system according to claim 28, wherein

the wavelength dispersion providing means includes a dispersion compensator for providing the optical signal wavelength dispersion sufficient to reduce the nonlinear effect, and

the wavelength dispersion compensating means includes an optical fiber having a dispersion value that compensates for the wavelength dispersion given by the dispersion compensator.

33. An optical transmission system according to claim 28, wherein

the wavelength dispersion providing means includes a first dispersion compensator for providing the optical signal wavelength dispersion sufficient to reduce the nonlinear effect, and

the wavelength dispersion compensating means includes a second dispersion compensator having a dispersion value opposite in sign to the dispersion value that the first dispersion compensator has.

34. An optical transmission system according to claim 33, wherein the first dispersion compensator has a positive dispersion value with respect to the optical signal.

35. An optical transmission system according to claim 33, wherein the first dispersion compensator has a negative dispersion value with respect to the optical signal.

36. An optical transmission system according to claim 28, further comprising optical signal characteristic adjusting means for adjusting a characteristic value of the optical signal and thereby optimizing the quality of the optical signal recognized by the optical receiver.

37. An optical transmission system according to claim 36, wherein the optical signal characteristic adjusting means includes a tunable light source whose emission wavelength is adjusted as the characteristic value of the optical signal to achieve the adjustment of the wavelength of the optical signal.

38. An optical transmission system according to claim 36, wherein the optical signal characteristic adjusting means includes variable-chirping means for adjusting as the characteristic value of the optical signal the amount of prechirping to be given to the optical signal generated by the optical transmitter.

39. An optical transmission system according to claim 36, wherein
the optical transmission line includes an optical fiber, and
the optical signal characteristic adjusting means includes means for adjusting as the characteristic value of
the optical signal the power of the optical signal entering the optical fiber.

5 40. An optical transmission system according to any one of claims 36 to 39, further including transmission characteristic
measuring means for measuring a transmission characteristic by evaluating the quality of the optical signal recog-
nized by the optical receiver, wherein

10 the optical signal characteristic adjusting means adjusts the characteristic value of the optical signal so that
the transmission characteristic measured by the transmission characteristic measuring means is best adjusted.

41. An optical transmission system according to claim 40, further comprising characteristic value sweeping means for
sweeping the characteristic value of the optical signal within a prescribed range, thereby making it possible to auto-
matically find the best characteristic value.

15 42. An optical transmission system according to claim 40, wherein the transmission characteristic measuring means
evaluates the quality of the optical signal by evaluating a bit-error, rate in the optical signal.

20 43. An optical transmission system according to claim 40, wherein the transmission characteristic measuring means
evaluates the quality of the optical signal by evaluating an eye pattern opening of the optical signal.

44. An optical transmission system according to claim 40, wherein the transmission characteristic measuring means
evaluates the quality of the optical signal by evaluating a Q value of the optical signal.

25 45. An optical transmission system according to claim 40, wherein the transmission characteristic measuring means
evaluates the quality of the optical signal by checking a parity bit in the optical signal.

30 46. An optical transmission system according to any one of claims 40 to 45, wherein
the optical transmission line includes an operating channel and a spare channel, and
the characteristic value sweeping means performs the characteristic value sweeping on the spare channel.

35 47. An optical transmission system comprising:
an optical transmitter for generating an optical signal;
an optical transmission line for transmitting the optical signal generated by the optical transmitter;
an optical receiver for recognizing the optical signal transmitted over the optical transmission line;
an optical amplification repeater, installed at an intermediate point along the optical transmission line, for
optically amplifying the optical signal being transmitted along the optical transmission line; and
a wavelength converter for converting the wavelength of the optical signal, optically amplified in the optical
amplification repeater.

40 48. An optical transmission system according to claim 47, wherein the optical transmitter includes a tunable light source
whose emission wavelength is adjusted to achieve the adjustment of the wavelength of the optical signal.

45 49. An optical transmission system according to claim 48, further including transmission characteristic measuring means
for measuring a transmission characteristic by evaluating the quality of the optical signal recognized by the optical
receiver, wherein

the wavelength converter and the tunable light source adjust the wavelength of output light so that the trans-
mission characteristic measured by the transmission characteristic measuring means is best adjusted.

50 50. An optical transmission system according to claim 49, further comprising wavelength sweeping means for sweeping
the wavelength of the output power within a prescribed range in the wavelength converter and the tunable light
source, thereby making it possible to automatically find the best wavelength.

55 51. An optical transmission system according to claim 49, wherein the transmission characteristic measuring means
evaluates the quality of the optical signal by evaluating a bit-error rate in the optical signal.

52. An optical transmission system according to claim 49, wherein the transmission characteristic measuring means
evaluates the quality of the optical signal by evaluating an eye pattern opening of the optical signal.

53. An optical transmission system according to claim 49, wherein the transmission characteristic measuring means evaluates the quality of the optical signal by evaluating a Q value of the optical signal.

54. An optical transmission system according to claim 49, wherein the transmission characteristic measuring means evaluates the quality of the optical signal by checking a parity bit in the optical signal.

55. An optical transmission system according to any one of claims 50 to 55, wherein
the optical transmission line includes an operating channel and a spare channel, and
the wavelength sweeping means performs the wavelength value sweeping on the spare channel.

56. A drift compensation circuit for optical modulators in an optical multiplexing system in which a plurality of optical signals modulated with baseband signals by a plurality of optical modulators are multiplexed together, comprising:
a plurality of drive circuits for amplitude-modulating the baseband signals with low-frequency signals before the baseband signals are supplied to the plurality of optical modulators;
an optical coupler for separating a portion of an optical multiplexed signal generated by multiplexing the plurality of optical signals;
an optical detector for converting the portion of the optical multiplexed signal separated by the optical coupler into an electrical signal; and
control means for generating a bias signal for the drift compensation of each of the optical modulators by phase-detecting the low-frequency signal components contained in the output of the optical detector with the low-frequency signals respectively used in the plurality of drive circuits.

57. A drift compensation circuit according to claim 56, wherein the plurality of optical signals are time-division multiplexed at the same wavelength.

58. A drift compensation circuit according to claim 57, wherein
the low-frequency signals used in the plurality of drive circuits are at different frequencies, and
the control means includes
a plurality of phase-detection/bias-supply circuits for generating bias signals for the respective optical modulators by phase-detecting the output of the optical detector with the low-frequency signals used in said plurality of drive circuits.

59. A drift compensation circuit according to claim 57, wherein
the control means includes
a first selector switch for supplying a low-frequency signal by time division to the plurality of drive circuits,
a phase-detection/bias-supply circuit for generating a bias signal for the drift compensation of the optical modulators by phase-detecting the output of the optical detector with the low-frequency signal, and
the second selector switch for distributing the bias signal generated by the phase-detection/bias-supply circuit to the respective optical modulators by operating in interlocking fashion with the first selector switch.

60. A drift compensation circuit according to claim 58 or 59, wherein the plurality of optical modulators are connected in parallel.

61. A drift compensation circuit according to claim 58 or 59, wherein the plurality of optical modulators are connected in series.

62. A drift compensation circuit according to claim 56, wherein the plurality of optical signals are wavelength-multiplexed at different wavelengths.

63. A drift compensation circuit according to claim 62, wherein
the low-frequency signals used in the plurality of drive circuits are at different frequencies, and
the control means includes
a plurality of phase-detection/bias-supply circuits for generating bias signals for the respective optical modulators by phase-detecting the output of the optical detector with the low-frequency signals used in said plurality of drive circuits.

64. A drift compensation circuit according to claim 62, wherein
the control means includes
a first selector switch for supplying a low-frequency signal by time division to the plurality of drive circuits,

a phase-detection/bias-supply circuit for generating a bias signal for the drift compensation of the optical modulators by phase-detecting the output of the optical detector with the low-frequency signal, and the second selector switch for distributing the bias signal generated by the phase-detection/bias-supply circuit to the respective optical modulators by operating in interlocking fashion with the first selector switch.

- 5 65. A drift compensation circuit according to claim 62, wherein
the optical detector includes a plurality of optical detectors, and
the control means includes
a wavelength separating device for separating the optical multiplexed signal, separated by the optical coupler,
10 into signals at different wavelengths, and for supplying the separated signals to the plurality of optical detectors, respectively, and
a plurality of phase-detection/bias-supply circuits for generating bias signals for the respective optical modulators by phase-detecting the low-frequency components output from the respective optical detectors with the low-frequency signals used in the respective drive circuits.
- 15 66. A drift compensation circuit according to claim 62, wherein the control means includes
a plurality of phase-detection/bias-supply circuits for generating bias optical signals for the respective optical modulators by phase-detecting the low-frequency components contained in the outputs of the respective optical modulators with the low-frequency signals used in the respective drive circuits,
20 a tunable optical filter installed between the optical coupler and the optical detector and whose transmission wavelength is switched by time division, and
a selector switch for distributing the output of the optical detector, to the respective phase-detection/bias-supply circuits by operating in synchronism with the transmission wavelength switching in the tunable optical filter.
- 25 67. A drift compensation circuit according to any one of claims 56 to 66, further comprising a sign-inverting circuit for switching an operation point of the optical modulator.
68. An optical transmission system comprising:
optical time-division multiplexing means for time-division multiplexing a plurality of optical signals;
30 an optical transmission line for transmitting an optical multiplexed signal generated by the optical time-division multiplexing means;
clock extraction means for extracting a clock signal for the original optical signals directly from the optical multiplexed signal transmitted over the optical transmission line; and
amplitude difference providing means for providing amplitude differences among the optical signals multi-
35 plexed on the optical multiplexed signal to be supplied to the clock extraction means and thereby enabling the clock extraction means to extract the clock signal.
69. An optical transmission system according to claim 68, wherein the amplitude difference providing means includes a plurality of light sources with different optical output powers, one for each of the plurality of optical signals.
- 40 70. An optical transmission system according to claim 68, wherein the amplitude difference providing means includes a light attenuator for attenuating at least one of the optical signals before being multiplexed by the optical time-division multiplexing means.
- 45 71. An optical transmission system according to claim 68, wherein the amplitude difference providing means includes an optical amplifier for amplifying at least one of the optical signals before being multiplexed by the optical time-division multiplexing means.
72. An optical transmission system according to claim 68, wherein the amplitude difference providing means includes
50 a plurality of optical modulators, provided with amplitude differences among drive signals, for producing the plurality of optical signals.
73. An optical transmission system according to claim 68, wherein the amplitude difference providing means includes a plurality of optical modulators, provided with bias voltage differences among drive signals, for producing the plurality
55 of optical signals.
74. An optical transmission system according to claim 68, wherein the amplitude difference providing means includes an optical switch for splitting light from a light source at a different splitting ratio.

75. An optical transmission system according to claim 68, wherein the amplitude difference providing means includes a plurality of optical modulators with different axes of polarization, for producing the plurality of optical signals, and a polarization-dependent optical device for passing the optical multiplexed signal therethrough.

76. An optical transmission system according to claim 75, wherein the polarization-dependent optical device is provided at the transmitting end of the light transmission line.

77. An optical transmission system according to claim 75, wherein the polarization-dependent optical device is provided at the receiving end of the light transmission line.

78. An optical transmitter comprising:
optical time-division multiplexing means for time-division multiplexing a plurality of optical signals; and
amplitude difference providing means for providing amplitude differences among the optical signals to be multiplexed on an optical multiplexed signal so that a clock signal for the original optical signals can be extracted directly from the optical multiplexed signal at the receiving end.

79. An optical transmitter according to claim 78, wherein the amplitude difference providing means includes a plurality of light sources with different optical output powers, one for each of the plurality of optical signals.

80. An optical transmitter according to claim 78, wherein the amplitude difference providing means includes a light attenuator for attenuating at least one of the optical signals before being multiplexed by the optical time-division multiplexing means.

81. An optical transmitter according to claim 78, wherein the amplitude difference providing means includes an optical amplifier for amplifying at least one of the optical signals before being multiplexed by the optical time-division multiplexing means.

82. An optical transmitter according to claim 78, wherein the amplitude difference providing means includes a plurality of optical modulators, provided with amplitude differences among drive signals, for producing the plurality of optical signals;

83. An optical transmitter according to claim 78, wherein the amplitude difference providing means includes a plurality of optical modulators, provided with bias voltage differences among drive signals, for producing the plurality of optical signals.

84. An optical transmitter according to claim 78, wherein the amplitude difference providing means includes an optical switch for splitting light from a light source at a different splitting ratio.

85. An optical transmitter according to claim 78, wherein the amplitude difference providing means includes a plurality of optical modulators with different axes of polarization, for producing the plurality of optical signals, and a polarization-dependent optical device for passing the optical multiplexed signal therethrough.

86. An optical transmission system comprising:
optical time-division multiplexing means for time-division multiplexing a plurality of optical signal channels;
means for appending identification information for identifying each optical signal channel, to an optical multiplexed signal generated by the optical time-division multiplexing means;
an identification information extraction circuit for extracting the identification information contained in the optical signal channel; and
a control circuit for changing output destinations so that each optical signal channel is output on a designated destination in accordance with the identification information extracted by the identification information extraction circuit.

87. An optical transmission system according to claim 86, further comprising:
a clock regenerating circuit for regenerating a clock signal for each optical signal channel from the optical multiplexed signal; and
an optical switch for separating each optical signal channel from the optical multiplexed signal in accordance with the clock signal regenerated by the clock regenerating circuit.

88. An optical transmission system according to claim 87, wherein
the identification information appending means appends identification data to a data signal transmitted on
each of the optical signals, and
the identification information extraction circuit extracts the identification data contained in the data signal
reconstructed from each optical signal channel.
89. An optical transmission system according to claim 88, wherein the control circuit changes output destinations by
changing connections between the output of each optical signal channel and the output destinations.
90. An optical transmission system according to claim 88, wherein the control circuit changes output destinations by
changing the phase of the clock signal supplied to the optical switch.
91. An optical transmission system according to claim 88, wherein the control circuit changes output destinations by
delaying or advancing the optical multiplexed signal input to the optical switch.
92. An optical transmission system according to claim 87, wherein
the identification information appending means superimposes a low-frequency signal on the optical multi-
plexed signal in a time slot designated for a specific optical signal channel, and
the identification information extraction circuit extracts the identification information by detecting the low-
frequency signal superimposed on the optical multiplexed signal.
93. An optical transmission system according to claim 92, wherein the identification information extraction circuit detects
the low-frequency signal from an electrical signal converted from each optical signal channel separated by the optical
switch.
94. An optical transmission system according to claim 92, wherein the identification information extraction circuit detects
the low-frequency signal from a current flowing to an optical/electrical converting device for converting each optical
signal channel separated by the optical switch into an electrical signal.
95. An optical transmission system according to any one of claims 92 to 94, further comprising a signal switching circuit
provided between outputs of the optical switch and output destinations, wherein the control circuit changes output
destinations by changing in the signal switching circuit connection relationships between the outputs of the optical
switch and the output destinations.
96. An optical transmission system according to any one of claims 92 to 94, wherein the control circuit changes output
destinations by changing the phase of the clock signal supplied to the optical switch.
97. An optical transmission system according to any one of claims 92 to 94, wherein the control circuit changes output
destinations by delaying or advancing the optical multiplexed signal input to the optical switch.
98. An optical receiver comprising:
an identification information extraction circuit for extracting identification information contained in an optical
signal channel; and
a control circuit for changing output destinations so that each optical signal channel is output on a designated
destination in accordance with the identification information extracted by the identification information extraction
circuit.
99. An optical receiver according to claim 98, further comprising:
a clock regenerating circuit for regenerating a clock signal for each optical signal channel from the optical
multiplexed signal;
an optical switch for separating each optical signal channel from the optical multiplexed signal in accordance
with the clock signal regenerated by the clock regenerating circuit.
100. An optical receiver according to claim 99, wherein
the identification information is appended as identification data to a data signal transmitted on the optical
signal, and
the identification information extraction circuit extracts the identification data contained in the data signal
reconstructed from each optical signal channel.

101.An optical receiver according to claim 100, further comprising a signal switching circuit provided between outputs of the optical switch and output destinations, wherein the control circuit changes output destinations by changing in the signal switching circuit connection relationships between the outputs of the optical switch and the output destinations.

102.An optical receiver according to claim 100, wherein the control circuit changes output destinations by changing the phase of the clock signal supplied to the optical switch.

103.An optical receiver according to claim 100, wherein the control circuit changes output destinations by delaying or advancing the optical multiplexed signal input to the optical switch.

104.An optical receiver according to claim 99, wherein
the identification information is superimposed as a low-frequency signal on the optical multiplexed signal in a time slot designated for a specific optical signal channel, and
the identification information extraction circuit extracts the identification information by detecting the low-frequency signal superimposed on the optical multiplexed signal.

105.An optical receiver according to claim 104, wherein the identification information extraction circuit detects the low-frequency signal from an electrical signal converted from each optical signal channel separated by the optical switch.

106.An optical receiver according to claim 104, wherein the identification information extraction circuit detects the low-frequency signal from a current flowing to an optical/electrical converting device for converting each optical signal channel separated by the optical switch into an electrical signal.

107.An optical receiver according to any one of claims 104 to 106, further comprising a signal switching circuit provided between outputs of the optical switch and output destinations, wherein the control circuit changes output destinations by changing in the signal switching circuit connection relationships between the outputs of the optical switch and the output destinations.

108.An optical receiver according to any one of claims 104 to 106, wherein the control circuit changes output destinations by changing the phase of the clock signal supplied to the optical switch.

109.An optical receiver according to any one of claims 104 to 106, wherein the control circuit changes output destinations by delaying or advancing the optical multiplexed signal input to the optical switch.

110.An optical demultiplexer comprising:
a clock regenerating circuit for regenerating a clock signal for each optical signal channel from an optical multiplexed signal;
an optical switch for separating each optical signal channel from the optical multiplexed signal in accordance with the clock signal regenerated by the clock regenerating circuit;
an identification information extraction circuit for extracting the identification information contained in the optical signal channel separated by the optical switch; and
a control circuit for changing output destinations so that each optical signal channel is output on a designated destination in accordance with the identification information extracted by the identification information extraction circuit.

111.An optical demultiplexer according to claim 110, wherein
the identification information is appended as identification data to a data signal represented by the optical signal, and
the identification information extraction circuit extracts the identification data contained in the data signal reconstructed from each optical signal channel.

112.An optical demultiplexer according to claim 111, further comprising a signal switching circuit provided between outputs of the optical switch and output destination, wherein the control circuit changes output destinations by changing in the signal switching circuit connection relationships between the outputs of the optical switch and the output destinations.

113.An optical demultiplexer according to claim 111, wherein the control circuit changes output destinations by changing the phase of the clock signal supplied to the optical switch.

114. An optical demultiplexer according to claim 111, wherein the control circuit changes output destinations by delaying or advancing the optical multiplexed signal input to the optical switch.

115. An optical demultiplexer according to claim 110, wherein
 5 the identification information is superimposed as a low-frequency signal on the optical multiplexed signal in a time slot designated for a specific optical signal channel, and
 the identification information extraction circuit extracts the identification information by detecting the low-frequency signal superimposed on the optical multiplexed signal.

116. An optical demultiplexer according to claim 115, wherein the identification information extraction circuit detects the low-frequency signal from an electrical signal converted from each optical signal channel separated by the optical switch.

117. An optical demultiplexer according to claim 115, wherein the identification information extraction circuit detects the low-frequency signal from a current flowing to an optical/electrical converting device for converting each optical signal channel separated by the optical switch into an electrical signal.

118. An optical demultiplexer according to any one of claims 115 to 117, further comprising a signal switching circuit provided between outputs of the optical switch and output destinations, wherein the control circuit changes output destinations by changing in the signal switching circuit connection relationships between the outputs of the optical switch and the output destinations.

119. An optical demultiplexer according to any one of claims 115 to 117, wherein the control circuit changes output destinations by changing the phase of the clock signal supplied to the optical switch.

120. An optical receiver according to any one of claims 115 to 117, wherein the control circuit changes output destinations by delaying or advancing the optical multiplexed signal input to the optical switch.

121. An optical transmitter comprising:
 30 optical time-division multiplexing means for time-division multiplexing a plurality of optical signal channels; and
 means for appending identification information for identifying each optical signal channel, to an optical multiplexed signal generated by the optical time-division multiplexing means.

122. An optical transmitter according to claim 121, wherein the identification information appending means superimposes a low-frequency signal on the optical multiplexed signal in a time slot designated for a specific optical signal channel.

123. An optical transmitter according to claim 122, wherein the identification information appending means includes a second optical modulator which is connected in series to an optical modulator for generating the specific optical signal channel, and to which the low-frequency signal is applied as a modulating signal.

124. An optical transmitter according to claim 122, wherein the identification information appending means includes a drive circuit for superimposing the low-frequency signal on a modulating signal for the specific optical signal channel, and for supplying the resulting signal as a modulating signal to an optical modulator for generating the optical signal channel.

125. An optical receiver for receiving an optical time-division multiplexed signal carrying a plurality of optical signals time-division multiplexed thereon and having a low-frequency signal superimposed thereon in a time slot designated for a specific optical signal, comprising:
 45 an optical switch for separating the optical time-division multiplexed signal into the respective optical signals;
 clock generating means for generating a clock signal for controlling the optical switch; and
 clock phase control means for performing control so that the clock signal generated by the clock generating means is phase synchronized to the optical time-division multiplexed signal, by using the low-frequency signal superimposed on the optical time-division multiplexed signal.

126. An optical receiver according to claim 125, wherein
 55 the clock generating means includes a timing regenerator for generating a clock signal by extracting a clock component from the received optical time-division multiplexed signal, and
 the clock phase control means includes
 a phase shifter for changing the phase of the clock signal output from the timing regenerator in accordance

with a phase control signal, and

a phase controller for generating a phase control signal for controlling the phase shifter to synchronize the clock signal to the optical time-division multiplexed signal by using the low-frequency signal.

5 **127.**An optical receiver according to claim 126, wherein

the phase controller includes

a light detecting element for converting one of the optical signals separated by the optical switch into an electrical signal,

an oscillator for outputting a signal of a prescribed frequency,

10 a synchronous detection circuit for phase-detecting the output of the light detecting element with the output of the oscillator,

a comparator for comparing the output of the synchronous detection circuit with a predetermined threshold value, and

15 an adder for adding the result of the comparison from the comparator to the output of the oscillator and for outputting the resulting sum as the phase control signal.

128.An optical receiver according to claim 127, wherein the phase controller further includes a band-pass filter, installed between the light detecting element and the synchronous detection circuit, for passing only the low-frequency signal component therethrough.

20 **129.**An optical receiver according to claim 127, wherein the comparator inverts the result of the comparison for output in accordance with a control signal.

130.An optical receiver according to any one of claims 126 to 129, wherein the timing regenerator includes

25 a level detector for detecting the level of the extracted clock component, and

a comparator for comparing the output of the level detector with a predetermined reference value, and for outputting an alarm signal when the output of the level detector is below the reference value.

131.An optical receiver according to claim 125, wherein

30 the clock generating means includes a voltage-controlled oscillator for generating a clock signal of a frequency that matches a control voltage, and

the clock phase control means includes a phase controller for generating a control voltage for controlling the voltage-controlled oscillator to synchronize the clock signal to the optical time-division multiplexed signal by using the low-frequency signal.

35 **132.**An optical receiver according to claim 131, wherein

the phase controller includes

a light detecting element for converting one of the optical signals separated by the optical switch into an electrical signal,

40 an oscillator for outputting a signal of a prescribed frequency,

a synchronous detection circuit for phase-comparing the output of the light detecting element with the output of the oscillator,

a comparator for comparing the output of the synchronous detection circuit with a predetermined threshold value, and

45 an adder for adding the result of the comparison from the comparator to the output of the oscillator and for outputting the resulting sum as the control voltage.

133.An optical receiver according to claim 132, wherein the phase controller further includes a band-pass filter, installed between the light detecting element and the synchronous detection circuit, for passing only the low-frequency signal component therethrough.

134.An optical receiver according to claim 132, wherein the comparator inverts the result of the comparison for output in accordance with a control signal.

55 **135.**An optical receiver according to any one of claims 131 to 134, further comprising

a low-frequency signal detection circuit for detecting the low-frequency component superimposed on the optical time-division multiplexed signal, and

a comparator for comparing a detected level from the low-frequency signal detection circuit with a predetermined reference value, and for outputting an alarm signal when the detected level is below the reference value.

Fig.1




Fig. 2




Fig. 3




Fig. 4




Fig. 5




Fig. 6




Fig. 7




Fig. 8





Fig. 9



F i g . 10




Fig.11




Fig. 12




Fig. 13




Fig. 14




Fig. 15




Fig. 16




Fig. 17




Fig. 18




Fig. 19





Fig. 20








Fig. 21

Fig. 22



F i g . 23

ZERO DISPERSION WAVELENGTH λ_0 

F i g . 24




Fig. 25




Fig. 26




Fig. 27




Fig. 28




Fig. 29




Fig. 30




Fig. 31




Fig. 32




Fig. 33




Fig. 34




Fig. 35




Fig.36




Fig.37




Fig.38




Fig.39




Fig.40





Fig.41






Fig.43




Fig.44




Fig.45




Fig.46




Fig.47




Fig.48




Fig.49




Fig.50




Fig.51




Fig.52




Fig.53




Fig.54




Fig. 55




Fig. 56




Fig.57




Fig.58




Fig. 59




Fig. 60




Fig.61




Fig. 62




Fig.63




Fig. 64




Fig. 65




Fig. 66




Fig. 67




Fig.68




Fig. 69






Fig.70









Fig.74




Fig.75




Fig. 76




Fig. 77




Fig. 78




Fig. 79




Fig. 80




Fig. 81




Fig. 82




Fig. 83




Fig. 84




Fig. 85




Fig. 86




Fig. 87




Fig.88




Fig. 89




Fig.90




Fig. 91




Fig. 92




Fig. 93




Fig. 94




Fig. 95





Fig.96



418, 420



Fig. 98




Fig.99




Fig.100




Fig.101




Fig. 102




Fig. 103




Fig.104




Fig.105




Fig. 106




Fig.107




Fig.108




Fig. 109




Fig. 110




Fig.111




Fig.112




Fig. 113




Fig.114




Fig. 115




Fig.116




Fig. 117




Fig. 118





Fig. 119






Fig.120

This Page Blank (uspto)